NASA-CR-169146 19820021468

FILTER FAILURE DETECTION FOR SYSTEMS WITH LARGE SPACE STRUCTURE DYNAMICS

Craig R. Carignan

June, 1982

SSL#1-82

(Under NASA Grant #NAG1-126)



LIBRARY COPY

AUG 3 0 1984

LIBRARY, NASA
HAMPTON, VIRGINIA

SPACE SYSTEMS LABORATORY
DEPT. OF AERONAUTICS AND ASTRONAUTICS
MASSACHUSETTS INSTITUTE OF TECHNOLOGY
CAMBRIDGE, MA 02139

NASA CR-169, 146

FILTER FAILURE DETECTION FOR SYSTEMS WITH LARGE SPACE STRUCTURE DYNAMICS

Craig R. Carignan

June, 1982

SSL#1-82

(Under NASA Grant #NAG1-126)

N87-29344

FILTER FAILURE DETECTION FOR SYSTEMS WITH LARGE SPACE STRUCTURE DYNAMICS

by

CRAIG RAYMOND CARIGNAN

Submitted to the Department of Aeronautics and Astronautics on May 14, 1982 in partial fulfillment of the requirements for the Degree of Master of Science in Aeronautics and Astronautics

ABSTRACT

A failure detection filter is applied to the detection of actuator and sensor failures on a free-free beam. Computer simulation tests are used to verify the filter design and study the effect of unmodeled modes on filter performance.

In actuator tests, the failure signal to spillover noise ratio was found to be greatest when the filter bandwidth was 5 rad/sec beyond the input frequency. Observation spillover, however, was found to vary widely in tests run under similar conditions (same input frequency and filter poles) but with different detector gains.

In sensor tests, the maximum signal-to-noise ratio for varying filter bandwidth depended upon the initial conditions placed on the unmodeled modes; the performance was good even for initial amplitudes on the first unmodeled mode 7.5% of that on the last modeled mode.

Data-sampling tests on filters designed for continuous data processing but employed in a sampled data mode revealed that adequate filter performance could be achieved only when the sampling rate was considerably beyond the natural frequency of the last system mode. Stability problems were encountered when the filter bandwidth became too high relative to the sampling rate.

The failure simulation tests suggest high sampling rates and sensor post-filtering to deal with the problems posed by sampling phase lag and observation spillover.

Thesis Supervisor: Wallace E. Vander Velde

Professor of Aeronautics and Astronautics

ACKNOWLEDGMENTS

This thesis is not the result of one person's work, but rather the result of advice and help from many people. In view of this, I would like to express my gratitude and thanks to the following people: my thesis advisor, Professor Wally Vander Velde, for his expert help and guidance throughout this thesis, Professor Rene Miller for his advice and encouragement in this and previous work, and Barbara for typing this thesis. My acknowledgments would not be complete without thanking my friends in the Space Systems Lab and my family for their encouragement and support.

I would also like to express my appreciation to the National Aeronautics and Space Administration for sponsoring this work under NASA Grant #NAG1-126, "Reliability Issues in Active Control of Flexible Space Structures."

Table of Contents '

		Page
1.	Introduction	7
2.	Detection Filter Theory	11
	2.1 Detection filter structure	11
	2.2 Failure models	14
	2.3 Detection filter design	17
	2.3.1 Fully measurable systems	18
	2.3.2 Partially measurable systems	19
	2.3.2.1 Detection generator	20
	2.3.2.2 Detector gain	22
	2.3.2.3 Detection space	24
	2.3.3 Sensor detectability	26
	2.3.4 Sets of events	30
	2.3.4.1 Actuator set	31
	2.3.4.2 Sensor set	31
	2.4 Two-mode Design Example	33
3.	Computational Design of Filter	38
	3.1 Orthogonal Reduction	38
	3.2 Input Failure Event Design	41
	3.2.1 Subroutine SEPDET	42
	3.2.2 Subroutine DETGEN	44
	3.2.3 Subroutine DGAIN	46
	3.3 Measurement failure event design	48

	Page
4. Application to Flexible Beam	51
4.1 NASA LaRC Experimental Beam	51
4.2 State equations for beam model	53
4.3 Failure detection filter design for the bear	n 56
4.4 Computer simulation of beam	58
4.4.1 Effect of model error	61
4.4.2 Sampled-data systems	75
5. Summary and Conclusions	81
Appendix A: Failure Detection Filter program (FDFIL)	84
Appendix B: Beam Simulation Program (FDSIM)	99
References	105

List	of Illustrations	Page
2.1	Failure detection filter block diagram	12
2.2	Eigenvalue assignment for detection filter	12
3.1	Flowchart for ORTRED	39
3.2	Flowchart for SEPDET	43
3.3	Flowchart for DETGEN	45
3.4	Flowchart for DGAIN	47
3.5	Sensor design process schematic	49
4.1	LaRC experimental beam set-up	52
4.2	SPAR beam modal frequencies and shapes	54
4.3	Output error transformation for sensor case	60
4.4	Sampled-data system/filter	60
4.5	Actuator failure for matched models	64
4.6	Model error effect for different filter models	65
4.7	Actuator tests for $\lambda^+=-10$ and $\omega_u^+=5,20,50$	68
4.8	Actuator tests for $\lambda = -15$ and $\omega_{\rm u} = 5,20,50$	69
4.9	Actuator tests for λ =-20 and $\omega_{\rm u}$ =5,20,50	70
.10	Sensor tests for various initial conditions	73
.11	Sensor tests for various filter bandwidths	74
.12	Data sampling tests for various sampling rates	78
1.13	Data sampling tests for various filter bandwidths	79

 $^{+\}lambda$ denotes filter poles (rad/sec)

 $[\]omega_{\text{u}}$ denotes input frequencies (rad/sec)

CHAPTER I

INTRODUCTION

With the advent of the space shuttle, aerospace engineers are contemplating the assembly and deployment of some very large space structures. Some structures under consideration include antennas and reflectors 100 meters in diameter and solar power satellites as large as 20 x 10 kilometers. Unlike the spacecraft of previous decades, these large structures have little inherent rigidity due to their low mass and large size. If the natural damping is not somehow increased, periodic disturbances such as gravity gradient and solar pressure which are close to the low natural frequencies of the structure will cause large dynamic overstresses that will eventually tear the structure apart.

The solar power satellite provides a good example of the types of overwhelming issues one would typically encounter in designing a control system for a large space structure. In order to adequately damp the many vibrational modes of the satellite, hundreds of thrusters and control moment gyros may be required to supplement passive damping. The system designer will have to decide how many actuators and sensors to use and where to place them on the structure. For example, rate gyro sensors and control moment gyros could be located almost anywhere on a truss-like structure. The control engineer will then have to decide what kind of control law to implement in order to maintain satisfactory structural rigidity. Obviously,

the control system cannot incorporate all the structural modes in its model, so care must be taken when controlling the disturbance-induced vibrations in the low frequency modes that the control does not spillover into the higher frequency unmodeled modes.

One factor which should not be overlooked in either the design or operation of the control system is the likelihood of some failures among actuators and sensors. For example, if the interval between maintenance visits is three years and the control system utilizes a total of 400 sensors and actuators each with an exponential distribution of time to failure with a mean time to failure of 100,000 hours, the expected number of failures in this interval is 92, and the probability that there will be no failures is 2×10^{-46} . Thus even with a very optimistic mean time to failure, it is virtually certain that failures will occur.

One of the major issues in dealing with component unreliability in control systems is how to detect a failure
and identify the failed component. This thesis is concerned
with one method of doing failure detection and identification
(FDI).

Many approaches to FDI have been used, the simplest of which involves triplication of components: a discrepancy between the signals of two like sensors signifies a failure, and comparison with the third determines which of the two has failed. Though simple, this method rapidly becomes costly and

even bulky for certain applications.

There are several approaches to FDI which require specification of failure modes ahead of time, but one which does not is generalized parity relations. This method uses sensor data from several time steps to detect failures rather than data from duplicate sensors at the same time instant. This approach has the obvious advantage of requiring fewer components, but it turns out to be very susceptible to plant disturbances and sensor noise. This detection routine also performs poorly when there is model error present, whether it be in the form of modal truncation or frequency errors.

A closed-loop method, the failure detection filter, can simultaneously monitor many different types of components, including sensors, actuators, and dynamic elements of the system. As with any other observer, the detection filter incorporates a linear-dynamic model of the system to estimate the true states of the system. Since the model receives the same control inputs as the true system, the outputs of the system and filter will normally match resulting in an output error of zero. However, when a component fails, the output error will no longer be zero, signifying that a failure has occurred. The failed component can then be identified by the fixed line or plane to which the output error is restricted by the detection filter.

The failure detection filter was first proposed by

Beard (1) in 1971 for deterministic systems. The theory was later expanded by Jones (2) to stochastic and sampled-data systems. Though not strictly valid for sampled-data systems, the detection filter will behave satisfactorily for sufficiently high sampling rates. Besides the application by Jones to a lateral mode autopilot, the failure detection filter was applied by VanderVelde (8) and Gerard (9) to the computer control of a guideway vehicle, and by Meserole (3) to fault-tolerant control of a turbofan engine. In neither of these previous applications was the filter designed to detect a sensor failure when the sensor output was not measuring a state directly. This is also the first time model error has been introduced into the filter.

The next chapter summarizes the main concepts of failure detection theory along with an analytic design procedure for the filter. Chapter 3 proposes a computational design procedure for the deterministic filter based mainly upon algorithms suggested in Appendix A of Beard (1). In Chapter 4, simulation results of actuator and sensor failures in deterministic systems are presented along with some results on data-sampling. Finally, some conclusions are outlined in Chapter 5.

CHAPTER II


FAILURE DETECTION FILTER THEORY

Detection filter theory is based upon vector-space concepts involving the state estimation errors generated by the filter following component failures. The major feature of the failure detection filter is that the output error is small while the system is functioning normally, and following the failure of a system component that error is significantly larger and appears only in a single direction or plane—that direction or plane indicating which component has failed. Thus the filter provides the basis for both detection of component failures and isolation of the faulty component. It is not necessary to specify in advance the possible modes of component failures.

In this chapter, the structure of the failure detection filter is first presented along with failure models for both actuator and sensor malfunctions and plant dynamics changes. The concept of failure "detectability" will then be introduced followed by the filter design theory for both fully measurable systems (rank C=n) and partially measurable systems (rank C<n). Finally, a two-mode beam example is used to illustrate the analytic design procedure.

2.1 Detection Filter Structure

The structure of the failure detection filter depicted in Fig. 2.1 is the same as that of any other state estimation






Fig. 2.2: Eigenvalue assignment for detection filter (number in parentheses indicates the number of eigenvalues of [A-DC] assigned with that gain).

filter monitoring a linear time invariant system. The difference is in the feedback gain D which is designed so that the output error will be held to a fixed direction or plane depending upon what component has failed. If D were the Kalman gain, the filter would minimize the mean square error between the states $\underline{x}(t)$ and the filter estimates $\hat{\underline{x}}(t)$ when noise is introduced into the system. For the case of an observer, $\hat{\underline{x}}(t)$ approaches $\underline{x}(t)$ asymptotically since no noise is present.

The system being monitored by the detection filter must be linear, time-invariant, and observable. The consequences of unobservability will be pointed out as they are encountered. In this work, mainly continuous inputs and measurements are considered.

The system is represented by the linear equations:

$$\dot{x}(t) = A\dot{x}(t) + B\dot{u}(t)$$

$$\dot{y}(t) = C\dot{x}(t)$$
(2.1-1)

where the state vector $\underline{\mathbf{x}}(t)$ has dimension n, the control vector $\underline{\mathbf{u}}(t)$ has m inputs, and the measurement vector $\underline{\mathbf{y}}(t)$ has p outputs. The filter incorporates the model:

$$\hat{\mathbf{x}}(t) = A \hat{\mathbf{x}}(t) + B \mathbf{u}(t) + D [\mathbf{y}(t) - \hat{\mathbf{y}}(t)]
\hat{\mathbf{y}}(t) = C \hat{\mathbf{x}}(t)$$
(2.1-2)

where \hat{x} is the filter state vector and $\hat{y}(t)$ the predicted measurement vector.

The state and measurement error dynamics are

$$\underline{e}(t) = [A-DC] \underline{e}(t)$$

$$\underline{e}(t) = C \underline{e}(t)$$
(2.1-3)

where $\underline{e}(t) \triangleq \underline{x}(t) - \frac{\hat{x}}{\hat{x}}(t)$ and $\underline{\xi}(t) = \underline{y}(t) - \frac{\hat{y}}{\hat{y}}(t)$. If the eigenvalues of A-DC have negative real parts, the steady state error will be zero so $\frac{\hat{x}}{\hat{x}}(t)$ will track $\underline{x}(t)$. Equation 2.1-3 is valid, however, only when $\{A,B,C\}$ of the filter in (2.1-2) match that of the true system represented by (2.1-1).

2.2 Failure Models

As mentioned above, (2.1-3) is valid only when the triplets {A,B,C} characterizing the system and filter match. If there is a component failure or change in plant dynamics, (2.1-1) will no longer represent the true system.

Consider an actuator j that has either failed completely or gone awry. The control vector, $\underline{\mathbf{u}}(t)$, is given by

$$\underline{U}(t) = \underline{U}_{c}(t) + \hat{\underline{e}}_{m_{j}} n(t) \qquad (2.2-1)$$

where $\underline{u}_{c}(t)$ is the commanded input (and filter input), $\hat{\underline{e}}_{m_{j}}$ is a unit vector in the jth direction of dimension m, and n(t) is a scalar time function depending upon the type of failure. The new state equation becomes

$$\dot{\mathbf{x}}(t) = \mathbf{A} \, \dot{\mathbf{x}}(t) + \mathbf{B} \, \mathbf{u}_{e}(t) + \dot{\mathbf{D}}_{i} \, \boldsymbol{n}(t) \tag{2.2-2}$$

where \underline{b}_{j} is the column of B corresponding to the jth actuator and $\eta(t)$ is some scalar time function. If the actuator fails completely in the off mode, $\eta(t)$ is simply minus the jth input, $-u_{c}$ (t), and the control effectiveness matrix for the true system is the same as for the filter except that the jth column of B is deleted.

Subtracting (2.1-2) from (2.2-2), the error equations become

$$\underline{\dot{e}}(t) = [A-DC]\underline{e}(t) + \underline{b}; n(t)$$

$$\underline{\dot{e}}(t) = [\underline{e}(t)]$$
(2.2-3)

The vector \underline{b}_j is called the "event vector" because it is the driving vector in the event of failure of the jth actuator. Detection filter theory will show that for any event vector \underline{f} , it is possible to find a D such that $\underline{\epsilon}(t)$ maintains a fixed direction in response to \underline{f} n(t).

Similarly, consider a sensor failure represented by the new measurement relation

$$y(t) = C_{\underline{X}}(t) + \hat{\underline{e}}_{p_i} \eta(t) \qquad (2.2-4)$$

where $\frac{\hat{e}}{p_j}$ is a unit vector in the jth direction and n(t) is an arbitrary scalar function of time. Complete failure of the jth sensor in the zero-output mode is modeled by letting $n(t) = -\frac{C^T}{j} \times (t)$, the predicted sensor output, and the measurement matrix for the true system is that of the filter with the jth row deleted.

The new error equations are generated analogously with (2.2-4) replacing y(t) in (2.1-1):

$$\underline{\dot{e}}(t) = [A-DC] \underline{e}(t) - \underline{\dot{d}}_{j} \eta(t)$$

$$\underline{\dot{e}}(t) = (\underline{e}(t) + \underline{\hat{e}}_{P_{j}} \eta(t))$$
(2.2-5)

Unlike the actuator case, the output error in the sensor failure

mode will have two directions: e_{p_j} due directly to the sensor failure and another component caused by the measurement error effect in the filter feedback loop. Even though D can be chosen to make e(t) due to e(t) unidirectional, this direction will usually not be e(t), and therefore the output error will span a plane rather than lie in a fixed direction.

Finally, let us consider changes in plant dynamics. Let the $ij^{\mbox{th}}$ element of A, for instance, change by the amount Δa_{ij} . The new state equation is:

$$\dot{\mathbf{x}}(t) = \mathbf{A}\mathbf{x}(t) + \mathbf{B}\mathbf{u}(t) + \Delta \mathbf{a}_{ij} \mathbf{x}_{j}(t) \, \hat{\mathbf{e}}_{n_{i}} \tag{2.2-6}$$

This model represents the effect of an alteration in the derivative of \mathbf{x}_{i} (t) due to dynamics involving \mathbf{x}_{j} (t). The error equations become

$$\underline{\hat{e}}(t) = \left[A - DC\right] \underline{\hat{e}}(t) + \Delta a_{ij} \chi_{j}(t) \underline{\hat{e}}_{n}; \qquad (2.2-7)$$

$$\underline{\hat{e}}(t) = C \underline{\hat{e}}(t)$$

Comparing this with Eq.(2.2-3), we see that the two pairs of equations have the same form with the scalar time function in this case being $\Delta a_{ij} x_j$ (t) and the new event vector as the n-dimensional i^{th} unit vector.

Actuator and plant dynamics failure models are, in fact, called "input failure models" since both can be represented as extraneous additive inputs to the system. When the failure term also appears in the measurement equation [as in Eq. (2.2-5) for sensor failures], the error equations are referred to as

the "measurement failure models." Only the actuator input and measurement failures will be considered in this work.

2.3 Detection Filter Design

The preceding discussion of failure models motivates the following definition of "detectability" found in Beard [1]: The event associated with the vector $\underline{\mathbf{f}}$ in the state error equation

$$\dot{\underline{e}}(t) = [A - DC]\underline{e}(t) + \underline{f}n(t) \qquad (2.3-1)$$

is "detectable" if there exists a gain matrix D such that:

- (i) $Ce_p(t)$ maintains a fixed direction in the output space $(e_p(t))$ is the settled-out solution of Eq. 2.3-1)
- (ii) All the eigenvalues of (A-DC) can be arbitrarily specified (this condition may be relaxed for fixed but stable eigenvalues).

If \underline{f} is detectable, then one can identify the failed component by checking the direction of the output error. For a measurement failure, the definition of detectability must be revised (see Section 2.3.3) and the output error is confined to a plane.

In the next several sections, the design of D for both fully measurable systems (rank C=n) and partially measurable systems (rank C=n) will be presented. Finding D for the first case is simple since the state vector $\underline{\mathbf{x}}(t)$ can be solved uniquely given $\underline{\mathbf{y}}(t)$. However, when the state vector is not fully measurable, the design of D is much more difficult and generates the need for a more advanced methodology.

2.3.1 Fully Measurable Systems

Let NS be the number of sensors or rows of C. To satisfy condition (ii) of detectability, choose A-DC to equal $-\sigma I$ where σ is a positive scalar constant. Then the eigenvalues of A-DC are all $-\sigma$ and D is given uniquely by

$$D = (A + \sigma I) C^{-1}$$
 (2.3-2)

for rankC=n=NS and nonuniquely as

$$D = (A + \sigma I)(C^{T}C)^{-1}C^{T}$$
 (2.3-3)

for rankC=n<NS.

For an actuator failure, $\underline{f} = \underline{b}_i$ and the solution of Eq. (2.2-3) is

$$\underline{e}(t) = \mathcal{L} \qquad \underline{e}(t_0)$$

$$+ \int_{t_0}^{t} -\sigma(t-\tau) \underline{b}; \eta(\tau) d\tau$$

$$(2.3-4)$$

The first term on the right is due to the initial conditions of the filter and will asymptotically approach zero for $\sigma > 0$. The second term is the driven or settled solution—it comes about because the filter models the ith actuator as working properly ($\underline{u}(t) = \underline{u}_{\sigma}(t)$) whereas in actuality it is not.

Since \underline{b}_{i} is constant, the settled-out solution is

$$\underline{e}_{s}(t) = \underline{b}_{i} \int_{t_{0}}^{t} e^{-\sigma(t-\tau)} n(\tau) d\tau \qquad (2.3-5)$$

Therefore, $\underline{e}_s(t)$ lies in the direction \underline{b}_i and a settled output error in the direction $C\underline{b}_i$ indicates a malfunction of the i^{th}

actuator.

Now consider a failure in the ith sensor as modeled by (2.2-4). Retaining the same choice for A-DC, the solution to (2.2-5) is

$$\underline{e}(t) = \mathcal{L}^{-\sigma(t-t_0)} \underline{e}(t_0)$$

$$-\underline{D} \hat{\underline{e}}_{P_i} \int_{t_0}^{t} e^{-\sigma(t-\tau)} n(\tau) d\tau$$
(2.3-6)

The settled output error is given by

$$\underline{\epsilon}_{s}(t) = -CD \, \hat{\underline{e}}_{P_{i}} \int_{t_{o}}^{t} e^{-\sigma(t-\tau)} \, \eta(\tau) \, d\tau + \hat{\underline{e}}_{P_{i}} \, \eta(t)$$

Therefore, an output error lying in the plane spanned by CD_{pi}^2 and $\frac{\hat{e}}{p_i}$ indicates a failure of the ith sensor.

Thus we see that finding D in the fully measurable case is indeed trivial and given by (2.3-2) for $A-DC = -\sigma I$. Choosing $A-DC = -\sigma I$ enabled the assignment of eigenvalues directly and also produced readily identifiable output error directions for component malfunctions because of the simple form of the state error transition matrix.

2.3.2 Partially Measurable Systems

Because C is not invertible in partially measurable systems, D cannot be solved by a simple relation like (2.3-2). What this means physically is that when an event occurs, an actuator failure for instance, the output error which results will not be uniquely associated with the state error caused by the event. Thus since the output error is the only accessible

signal, D will not be unique in satisfying the conditions of detectability. It will therefore be necessary to explore the relation of D to the space spanned by state errors during an event.

2.3.2.1 Detection Generator

Consider the system equations (2.1-1) for the case of a single actuator:

$$\dot{\mathbf{x}}(t) = \mathbf{A}\mathbf{x}(t) + \mathbf{b}; \mathbf{u}(t) \tag{2.3-7}$$

From linear systems theory, the controllable space of u(t), [the space of states which are possible to reach from the origin using u(t)] is the range space of

$$W_{i} \triangleq \left[\begin{array}{ccc} \underline{b}_{i} & A\underline{b}_{i} & \cdots & A^{n-1}\underline{b}_{i} \end{array} \right]$$
 (2.3-8)

The event vector \underline{f} has a similar meaning with respect to the error space $\underline{e}(t)$ of (2.3-1). In this case, the error space that can be reached in the event of a failure is the range space of

$$W_{\mathfrak{t}} = \left[\underbrace{f} \left(A - DC \right) \underbrace{f} \cdots \left(A - DC \right)^{n-1} \underbrace{f} \right] \qquad (2.3-9)$$

or the "detection space" of \underline{f} . The output error space therefore spans CW_f , and condition (i) of detectability is satisfied only if the rank of CW_f is 1. Any matrix D which satisfies this condition is called a "detector gain" for f.

Associated with \underline{f} is another vector also in $W_{\underline{f}}$ defined by the following theorem proven in Beard:

Detection generator theorem -

If (i) (A,C) is an observable pair

(ii)
$$rank W_f = k$$

(iii)
$$rank CW_f = 1$$

Then there exists an n-vector \underline{q} in W_f such that

$$[C: CA: \cdots : CA^{\kappa-2}]g = 0$$

$$CA^{\kappa-1}g \neq 0$$
(2.3-10)

and

The latter relation in (2.3-10) guarantees that the controllable space of \underline{g} with respect to (A-DC) is of dimension k and so matches the controllable space of \underline{f} . Note also that the first equation in (2.3-10) yields

$$[g](A-DC)g] \cdot \cdot \cdot |(A-DC)^{k-1}g]$$

$$= [g]Ag] \cdot \cdot \cdot |A^{k-1}g]$$
(2.3-11)

so the set of vectors $\{\underline{q}, \underline{Aq}, \ldots, \underline{A^{k-1}q}\}$ form a basis for the controllable space of \underline{f} .

Since \underline{f} is the generator of $W_{\underline{f}}$, it can be expressed as

$$\underline{f} = \alpha_1 \underline{q} + \alpha_2 A \underline{q} + \dots + \alpha_K A^{K-1} \underline{q}$$
 (2.3-12)

where the α_i are scalars. Premultiplying by C and using (2.3-10),

$$C\underline{f} = \alpha_{\kappa} CA^{\kappa-1}\underline{q}$$
 (2.3-13)

If $C\underline{f} \neq 0$, then $\alpha_k \neq 0$, and since the magnitude of \underline{g} is not restricted by (2.3-10), we are free to choose $\alpha_k = 1$.

If in general, for some nonnegative integer μ ,

$$\begin{array}{ll}
C A^{j} \underline{f} = \underline{O} & j = 0, \dots, \mu - 1 \\
C A^{\mu} \underline{f} \neq 0
\end{array}$$

then

$$\alpha_{k-j} = 0$$
 for $j = 0, ..., \mu-1$
 $\alpha_{k-\mu} \neq 0$ (2.3-15)

and <u>g</u> is chosen so that $\alpha_{k-\mu}=1$. The fact that (A,C) is an observable pair will guarantee that (2.3-14) holds for $\mu \le k-1$. Using (2.3-15) in (2.3-12) yields

$$f = d, g + ... + d_{k-\mu-1} A^{k-\mu-2} g + A^{k-\mu-1} g$$
 (2.3-16)

where μ satisfies (2.3-14).

The n-vector \underline{g} which satisfies (2.3-10) and (2.3-16) is called a k^{th} order "detection generator" for \underline{f} . The detection generator theorem has shown that as long as (A,C) is an observable pair, there always exists a detection generator associated with a detector gain.

2.3.2.2 Detector Gain

The preceding development of the detection generator serves as a prelude to the following theorem from which D can be found:

Detector gain theorem -

If (i) (A,C) is an observable pair

(ii) rank
$$W_f = k$$

(iii) rank
$$CW_f = 1$$

and k eigenvalues of [A-DC] associated with $\mathbf{W}_{\mathbf{f}}$ are given by the roots of

$$S^{k} + P_{k}S^{k-1} + ... + P_{2}S + P_{1} = 0$$
 (2.3-17)

Then D is a solution of

$$DCA^{k-1}f = p_1g + p_2Ag + ... + p_kA^{k-1}g + A^kg$$
 (2.3-18)

where p_i are scalars and g is a k^{th} order detection generator for f

Conversely, any D satisfying (2.3-18) is a detector gain for \underline{f} and k eigenvalues of [A-DC] associated with $W_{\underline{f}}$ are given by the roots of (2.3-17).

This theorem is perhaps the main result of detection filter theory and follows mainly from the Cayley-Hamilton Theorem applied to [A-DC] and invoking (2.3-11).

Premultiplying (2.3-16) by CA^{μ} and using (2.3-10) yields

$$CA^{\mu}\underline{f} = CA^{\kappa-1}\underline{q} \tag{2.3-19}$$

which when substituted into (2.3-18) gives

$$DCA^{\mu}f = p_1g + ... + p_{\kappa}A^{\kappa-1}g + A^{\kappa}g$$
 (2.3-20)

where $\mu=0$ corresponds to the condition $C\underline{f}\neq 0$. The rest of the results will be derived for $\mu=0$, but the corresponding general results can be obtained by simply replacing \underline{f} by $A^{\mu}\underline{f}$.

The general solution of (2.3-20) is expressible in the form

$$D = D_P + D_H$$

where (2.3-21)

$$D^{\mu} = \partial^{\mu} \left[(C\bar{t})_{\perp} C\bar{t} \right]_{-} (C\bar{t})_{\perp}$$

$$D^{\mu} = \partial^{\mu} \left[(C\bar{t})_{\perp} C\bar{t} \right]_{-} (C\bar{t})_{\perp}$$

with \underline{q}_D being the right side of (2.3-20) and D' an arbitrary

matrix the same dimensions as D. D_p is the particular solution of D and satisfies (2.3-20). Therefore, D_p is alone sufficient to guarantee condition (i) of detectability and specify k eigenvalues of [A-DC]. D_H is the homogeneous solution of D, i.e., $D_HC\underline{f}=\underline{0}$, and represents the freedom left in D after having satisfied (2.3-20). Condition (ii) of detectability will be satisfied only if the remaining n-k eigenvalues of [A-DC] can be assigned using D'.

2.3.2.3 Detection Space

Beard proposes the following auxiliary lemma to show that the remaining eigenvalues of [A-DC] can be assigned (the actual assignment of these remaining eigenvalues is discussed in Chapter 3):

Auxiliary detector gain lemma -

For A', C', and D' given by

$$A' = A - q_{D} \left[(C_{\underline{f}})^{T} C_{\underline{f}} \right]^{-1} (C_{\underline{f}})^{T} C$$

$$C' = C - C_{\underline{f}} \left[(C_{\underline{f}})^{T} C_{\underline{f}} \right]^{-1} (C_{\underline{f}})^{T} C$$

$$D' \text{ orbitionly}$$

$$(2.3-22)$$

The number of eigenvalues of [A'-D'C'] = [A-DC] that can be specified by D' is q' = rank M' where

$$M' = [C' | C'A' | \cdots | C'A'^{n-1}]^T$$
 (2.3-23)

This lemma shows that the total number of eigenvalues of [A-DC] that can be specified while constraining D to be a detector gain is k + q'. Therefore, condition (ii) of detectability will be satisfied only if n = k + q'.

The next lemma shows that M' does not depend upon the particular detection generator used or its order k even though it

appears to through A':

Detection space theorem -

For K defined by

$$K = A - A f [(Cf)^T Cf]^{-1} (Cf)^T C$$

M' is also equivalent to

$$M' = \begin{bmatrix} C' & C' & K' & \cdots & C' & K'' \end{bmatrix}^T$$
(2.3-24)

Since C' and K depend only on A, C, and \underline{f} , M' is the same regardless of what detection generator is used. Thus the number of eigenvalues of [A-DC] that can be specified while constraining D to be a detector gain is always the same no matter what \underline{g} is used to find $D_{\underline{p}}$. The null space of M' is called the "detection space" of \underline{f} and corresponds to the controllable space of \underline{f} with respect to [A-DC]. The dimension of the detection space is called the "detection order" $\mathcal V$, and a detection generator of order $\mathcal V$ is called the "maximal generator" for \underline{f} .

The rank of the null space of M' is $\sqrt{\ }=$ n - q', so if q' eigenvalues of [A-DC] are assignable using D', then a detection generator of order $k=\sqrt{\ }$ is needed to assign all the eigenvalues and satisfy condition (ii) of detectability. Beard shows that if (A,C) is an observable pair, \underline{f} will have a maximal generator and it is unique. Thus, the event \underline{f} is guaranteed detectable if (A,C) is observable. Beard also shows that although observability is necessary to satisfy condition (ii) of detectability, it is not necessary to satisfy condition (i) if \underline{f} is in the observable space. The number of assignable eigenvalues in this case is the rank of the observability matrix M defined by (2.3-23) without

the primes. Therefore, if one is willing to accept n-rank M unassignable eigenvalues, every observable event is detectable in this weaker sense for the unobservable pair (A,C).

The following theorem summarizes the conditions for detectability:

Detectability Theorem -

Every vector in the state space Rⁿ is detectable if and only if (A,C) is an observable pair.

2.3.3 Sensor Detectability

In deriving (2.2-5), we noted a fundamental difference between measurement and input failures; whereas an actuator failure only drives the state error through the event vector \underline{b}_{j} , a sensor failure drives the state error through the output feedback term as well as the event vector \underline{d}_{j} . Consequently, the best the filter can do is constrain the output error to a two-dimensional plane. Even though this was shown only for the fully measurable case, Beard proves this is true for partially measurable systems as well.

Because the event vector \underline{d}_j is at the discretion of the designer and is not related at all to the sensor itself, the theorems in the previous sections are not directly applicable. Instead, the ith row of C will be associated with a sensor failure just as the ith column of B was associated with an actuator failure. This motivates the following modified definition of detectability for sensor failures:

The ith row of C, \mathcal{L}_{i}^{T} , is "sensor detectable" if there exists a gain matrix D such that:

- (i) $\underline{\epsilon}_p$ (t) is constrained to a 2D-plane (where $\underline{\epsilon}_p$ (t) is the settled-out solution of (2.2-5))
- (ii) the eigenvalues of [A-DC] can be specified arbitrarily The following theorem is the sensor counterpart to the Detectability Theorem:

Sensor Detectability Theorem -

If (A,C) is an observable pair and $\underline{c_i}^T$ is linearly independent of all the other rows of C, then $\underline{c_i}^T$ is sensor detectable.

The filter design procedure for sensors is stated in two steps which also serve as a basis for the proof of this theorem:

(1) first choose D to be a detector gain for \underline{f} , by making it a solution of (2.3-20), where

$$Cf_i = \hat{\mathbf{e}}_{P_i} \tag{2.3-25}$$

(2) then make D' a detector gain for \underline{d}_i with respect to the pair (A',C')

Before proving the theorem, we first outline two implications of (2.3-25). First, the existence of \underline{f} is guaranteed because $\underline{c_i}^T$ is linearly independent of the other rows of C (pseudoinverse of C exists). Therefore by the detectability theorem, \underline{f} is detectable. Second, $\underline{d_i}$ is now fixed because (2.3-20) becomes

$$\underline{d}_{i} = P_{i}q + \dots + P_{n}A^{n}q + A^{n}q \qquad (2.3-26)$$
 where ν is the detection order of \underline{f} , and \underline{g} is its maximal

generator. Assume for the moment that \underline{d} , lies in the observable sp

Assume for the moment that \underline{d}_i lies in the observable space of (A',C') and prove that condition (i) of sensor detectability

holds. This assumption plus the detectability theorem guarantee that the detector gain D' exists for the event \underline{d}_i with respect to (A',C'). Furthermore, $C'\underline{e'}_s(t)$ lies in a fixed direction where $\underline{e'}_s(t)$ is the settled-out solution of

$$\dot{e}'(t) = (A' - D'C') \,\underline{e}'(t) - \underline{d}_i \, \eta(t) \tag{2.3-27}$$

Since A'-D'C' is equal to A-DC, $\underline{e}'_{S}(t)$ is the settled state error for the pair (A,C) using the gain D as well. This fixed direction can therefore be expressed as

$$C'e_{5}(t) = \chi_{A} m_{A}(t)$$
 (2.3-28)

where \underline{y}_d is this fixed direction and m_d (t) is a scalar function depending upon n(t).

From (2.3-22), C' is given by

$$C' = C - \hat{\mathbf{e}}_{P} : C^{T}$$
 (2.3-29)

so that

$$Ce'_{s}(t) = \chi_{d} m_{d}(t) + \hat{e}_{p}; C'_{t} e'_{s}(t)$$
 (2.3-30)

From (2.2-5), the output error is

$$\xi(t) = \chi_{d} m_{d}(t) + \hat{\underline{e}}_{P} \cdot [n(t) + \underline{c}_{i}^{T} \underline{e}_{s}^{i}(t)]$$
(2.3-31)

Since the quantity in brackets is a scalar, $\underline{\epsilon}(t)$ lies in the plane spanned by \underline{y}_d and $\hat{\underline{e}}_p$. Beard shows that \underline{y}_d can be broken up into a component in the $\hat{\underline{e}}_p$ direction and the $CK^{\lambda}A\underline{f}$ direction, where K is given in (2.3-24) and λ is the lowest integer such that $CK^{\lambda}A\underline{f} \neq 0$. Thus the output error lies in the plane formed by $\hat{\underline{e}}_p$ and $CK^{\lambda}A\underline{f}$.

Let us now relax the assumption that \underline{d}_i lies in the observable space of (A'C'). The observability matrix is given by M' defined

by (2.3-23), so if $\underline{d_i}$ is unobservable, M' $\underline{d_i} = \underline{0}$. Therefore, $\underline{d_i}$ lies in the nullspace of M', or equivalently, in the detection space of \underline{f} . As Beard shows, every vector contained in the detection space of \underline{f} has the same detection order and detection space as \underline{f} , so D is a detector gain for $\underline{d_i}$ as well as for \underline{f} (i.e., $\underline{d_i}$ is detectable in the traditional sense). Therefore, the second step of making D' a detector gain for $\underline{d_i}$ is unnecessary, and $\underline{Ce_s^i}(t)$ will lie in a fixed direction.

Finally, it remains to show that all the eigenvalues of A-DC are assignable. When making D a detector gain for \underline{f} , \sqrt{t} eigenvalues can be assigned using (2.3-17) since (A,C) is an observable pair. If \underline{d}_i is unobservable with respect to (A',C'), then D' is unconstrained, and the remaining $n-\sqrt{t}$ eigenvalues are assignable by the free choice of D' by the auxiliary detector gain lemma. Now if \underline{d}_i is observable for (A',C'), a total of only n-rank M' eigenvalues can be assigned while making D' a detector gain for \underline{d}_i and using D", the auxiliary detector gain for D' (D' is the auxiliary detector gain for D). The remaining \sqrt{t} eigenvalues are associated with the unobservable space of (A',C') which coincides with the detection space of \underline{f} and have already been specified by making D a detector gain for \underline{f} . Thus all the eigenvalues are assignable.

One last remark helps to simplify the computation of D'. D' can be made a detector gain for \underline{Af} instead of $\underline{d_i}$ because $\underline{Af} \equiv \underline{d_i} \pmod{E}$, where E denotes the unobservable space of (A',C'). This means that the difference $\underline{Af} - \underline{d_i}$ lies in E. With this substitution, the need to compute (2.3-26) is avoided.

2.3.4 Sets of Events

Up to this point, we have only concerned ourselves with detectability of a single event. Now consider the set of event vectors $\{\underline{f}_1,\ldots,\underline{f}_r\}$. The set is considered "mutually detectable" if there exists a D that satisfies the conditions of detectability for all r events. If the set of vectors satisfy

rank CF = r
$$F \triangleq \left[A^{\mu_1} f_1, \dots, A^{\mu_r} f_r \right] \qquad (2.3-32)$$

with μ defined for each \underline{f}_i as in (2.3-14), then the events are called "output separable." Two events are not output separable if the output error for both events lie in the same direction. All sets of events considered in this work were output separable.

A necessary and sufficient condition for a set of output separable events to be mutually detectable is given by the following theorem:

Group Detection Theorem -

The output separable vectors $\{\underline{f}_1,\ldots,\underline{f}_r\}$ are mutually detectable if and only if the sum of the individual detection orders of the \underline{f}_i is equal to the group detection order given by the dimension of the nullspace of M'_G , (n-rank M'_G), where M'_G is defined as M' in (2.3-24) with \underline{f} replaced by F.

The basic outline of the proof proceeds as follows. Since the set of events $\{\underline{f}_1,\ldots,\underline{f}_r\}$ are output separable, the events have nonintersecting subspaces (shown by Beard), and thus $\boldsymbol{\nu}_i$ eigenvalues can be specified for each \underline{f}_i while satisfying (2.3-20). An additional q_G^i = rank \underline{M}_G^i eigenvalues can be specified

by free choice of D'. Therefore, condition (ii) of detectability is satisfied if and only if $\sum \nu_i = n - q_G^i$. If the set is not mutually detectable, $n - q_G^i - \sum \nu_i$ eigenvalues cannot be controlled.

2.3.4.1 Actuator Set

The design of the detection filter for a set of actuator events proceeds as follows:

- (1) determine the maximal generator for each \underline{b}_i using (2.3-10)
- (2) form F as defined in (2.3-32) and divide the set up into output separable subsets
- (3) subdivide the set further, if necessary, until the subsets are also mutually detectable
- (4) solve (2.3-20) for each \underline{b}_i to make D a detector gain for F while using the pis to specify Σv_i eigenvalues
- (5) specify the remaining eigenvalues of A-DC using D'

Step 3 is unnecessary if the uncontrollable eigenvalues resulting from nonmutual detectability are satisfactory. Beard generates an algorithm that aids in finding these fixed eigenvalues and can also expedite step 3.

2.3.4.2 Sensor Set

One design method for a filter detecting sensor failures proceeds as follows:

- (1) for each \underline{c}_{i}^{T} , determine \underline{f}_{i} such that $\underline{C}_{i} = \underline{e}_{p_{i}}$ where the sensors are linearly independent
- (2) form F as in (2.3-32) and subdivide into mutually detectable sets (events are automatically output separable by step 1)

- form the set of vectors $\left\{ \underbrace{A\underline{f}_1, \ldots, A\underline{f}_k}_{1} \right\}$ where $F_{k_1} = \left\{ \underbrace{f}_{1}, \ldots, \underbrace{f}_{k_1} \right\}$ is the set resulting from step 2; let A' and C' be defined as in (2.3-22) with \underline{f} replaced by F_{k_1} ; categorize the $A\underline{f}_{i}$ as follows, and remove those events falling under (iii):
 - (i) M' Af; ≠ 0
 - (ii) M' Af; = 0; rank {CAf; CA' Af; ..., CA'" Af; }=1
 - (iii) M' Af; = Q; rank { CAfi, CA'Afi,..., CA'n-'Afi}>1
- let $F_{k_2} = \{\underline{f_1}, \dots, \underline{f_k}\}$ be the set resulting from step 3; let A' and C' be defined as in (2.3-22) with \underline{f} replaced by F_{k_2} ; repeat step 2 with A, C, and $\underline{f_i}$ replaced by A', C', and the $\underline{Af_i}$ in category (i); remove $\underline{Af_i}$'s until the $\underline{Af_i}$ are mutually detectable with respect to (A',C'); if any $\underline{Af_i}$ are removed, some $\underline{Af_i}$ may move from category (ii) to (i) and mutual detectability with the new members must be rechecked
- (5) solve (2.3-20) for each \underline{f}_i in the set $\mathbf{F}_{\mathbf{k}_3}$ resulting from step 4 to make D a detector gain for $\mathbf{F}_{\mathbf{k}_3}$ while specifying $\Sigma\,\mathcal{N}_i$ eigenvalues
- (6) solve (2.3-20) for each $A\underline{f}_i$ in the set F_{k_3} to make D' a detector gain for AF_{k_3} with respect to (A',C') while specifying $\Sigma \nu_i$ eigenvalues (ν_i denotes the maximum order a detection generator for $A\underline{f}_i$ can have)
- (7) use D" to specify the remaining eigenvalues of
 (A'-D'C') = A-DC [D" is to D' as D' is to D in section
 2.3.4.1.]

A few remarks concerning step 3 are in order. If category (i) is the case, $A\underline{f}_{-i}$ does not lie in the unobservable space of C' with respect to A' and thus $A\underline{f}_{-i}$ is detectable. For categories (ii) and (iii), $A\underline{f}_{-i}$ does lie in the unobservable space so $A\underline{f}_{-i}$ is not detectable; this is of no consequence, however, if D is a detector gain for $A\underline{f}_{-i}$ as well as \underline{f}_{-i} as is the case for category (ii) (see end of Section 2.3.3). The rank test given in step 3 determines whether the given sequence of vectors lie in a fixed direction—if they do, category (ii) applies.

The assignment of eigenvalues in the last three steps is depicted in Fig. 2.2: $\Sigma \nu_i$ eigenvalues are assigned using D_p and $n - \Sigma \nu_i$ are specified using D'; of the $n - \Sigma \nu_i$, $\Sigma \nu_i$ are assigned using D'_p and the rest using D'_H which depends on D'' (subscripts P and H denote p rticular and homogeneous solutions, respectively).

2.4 Two-mode Design Example

As a simple example of the analytic design procedure for the failure detection filter, consider the normal mode equations

$$\ddot{Y}_r(t) + \omega_r^2 \dot{Y}_r(t) = G_r u(t)$$
 $r = 1, 2, ...$ (2.4-1)

where Ψ_r represents the amplitude of the r^{th} mode, ω_r its natural frequency, and G_r the amplitude of the input u. In a single degree of freedom mass-spring system, for instance, Ψ is just the displacement x and ω^2 is the spring constant k divided by the mass m.

In particular, consider the system of equations for two flexible modes of a beam given in the form (2.1-1):

$$\begin{bmatrix} \dot{\gamma}_{i} \\ \dot{\gamma}_{i} \\ \dot{\gamma}_{z} \\ \ddot{\gamma}_{z} \end{bmatrix} = \begin{bmatrix} 0 & 1 & 0 & 0 \\ -\omega_{i}^{2} & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & -\omega_{z}^{2} & 0 \end{bmatrix} \begin{bmatrix} \gamma_{i} \\ \dot{\gamma}_{i} \\ \dot{\gamma}_{z} \\ \dot{\gamma}_{z} \end{bmatrix} + \begin{bmatrix} 0 & 0 \\ \frac{1}{M}\phi_{i}(\epsilon_{i}) & \frac{1}{M}\phi_{i}(\epsilon_{z}) \\ 0 & 0 \\ \frac{1}{M}\phi_{z}(\epsilon_{i}) & \frac{1}{M}\phi_{z}(\epsilon_{z}) \end{bmatrix} \begin{bmatrix} u_{i} \\ u_{z} \end{bmatrix}$$

$$(2.4-2)$$

$$\begin{bmatrix} \gamma_1 \\ \gamma_2 \end{bmatrix} = \begin{bmatrix} 0 & \phi_1(\alpha_1) & 0 & \phi_2(\alpha_1) \\ 0 & \phi_1(\alpha_2) & 0 & \phi_2(\alpha_2) \end{bmatrix} \begin{bmatrix} \psi_1 \\ \psi_1 \\ \psi_2 \\ \psi_2 \\ \psi_2 \end{bmatrix}$$

where force actuators at ϵ_1 , ϵ_2 and translation rate sensors at α_1 , α_2 are used $[\phi_i(\mathbf{x}_j)]$ represents value of the ith mode shape at \mathbf{x}_i .

To simplify the design procedure, Beard shows that if the matrix A is replaced by

$$\overline{A} = A - \overline{D}C$$
 (2.4-3)

with \overline{D} arbitrary, the detector gain is unaffected. Following this suggestion, let's replace A by the simpler form

$$\overline{A} = \begin{bmatrix} 0 & 0 & 0 & 0 \\ -\omega_1^2 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 \\ 0 & 0 & -\omega_1^2 & 0 \end{bmatrix}$$
 (2.4-4)

Now let's proceed to design a detection filter that can detect failures of either actuator #1 or actuator #2. The two event vectors for this case are \underline{b}_1 and \underline{b}_2 , the two columns of B. If the two actuators are not both at the same location or placed symmetrically about the center (for a free-free beam), the directions $C\underline{b}_1$ and $C\underline{b}_2$ will be linearly independent and thus output separable. To determine mutual detectability, the detection order for each \underline{f} must be found.

For an appropriate choice of D, K is found from (2.3-24) to be equal to \overline{A} , and C' using (2.3-22) becomes

$$C' = \begin{bmatrix} O & C_1 & O & C_3 \\ O & C_2 & O & C_4 \end{bmatrix}$$
 (2.4-5)

where the C_i 's are functions of the elements of $C\underline{b}$ and C. Now form

The two rows of C' are linearly dependent so that the rank of M' is 2 and thus the detection order of \underline{f} is 2 for both \underline{b}_1 and \underline{b}_2 . Since M' is the null matrix, the group detection order is four and the events are mutually detectable.

The maximal generator for \underline{f} is second order in this case and so must satisfy the set (2.3-10):

$$\begin{array}{c}
Cq = Q \\
CAq = Q
\end{array}$$

If g is represented by $[g_a g_b g_c g_d]^T$, the first of (2.4-7) becomes

where \emptyset_{ij} is used to denote $\emptyset_i(\alpha_j)$. Since we have assumed linear independence of the sensors,

$$\begin{vmatrix} \phi_{11} & \phi_{21} \\ \phi_{12} & \phi_{22} \end{vmatrix} \neq 0 \tag{2.4-9}$$

and we must accept the trivial solution $g_b = g_d = 0$. The second equation in (2.4-7) transforms into

$$\begin{bmatrix} g_{\alpha} \\ g_{c} \end{bmatrix} = \begin{bmatrix} -\omega_{1}^{2} \phi_{11} & -\omega_{2}^{2} \phi_{21} \\ -\omega_{1}^{2} \phi_{r2} & -\omega_{1}^{2} \phi_{22} \end{bmatrix} \begin{bmatrix} \phi_{11} & \phi_{21} \\ \phi_{12} & \phi_{22} \end{bmatrix} \begin{bmatrix} \beta_{1} \\ \beta_{2} \end{bmatrix}$$
(2.4-10)

with β_1 and β_2 denoting the nonzero elements of \underline{b} , and (2.4-9) guaranteeing existence of the inverted matrix.

All that remains is to solve (2.3-20) with k = 2 for each event. If λ is chosen for all the filter eigenvalues, $p_1 = \lambda^2$ and $p_2 = -2\lambda$. The particular solution of D is found to be

$$D_{p} = \begin{bmatrix} (p_{1} - \omega_{1}^{2}) g_{1\alpha} & (p_{1} - \omega_{1}^{2}) g_{2\alpha} \\ -p_{2} \omega_{1}^{2} g_{1\alpha} & -p_{2} \omega_{1}^{2} g_{2\alpha} \\ (p_{1} - \omega_{2}^{2}) g_{1c} & (p_{1} - \omega_{2}^{2}) g_{2c} \\ -p_{2} \omega_{2}^{2} g_{1c} & -p_{2} \omega_{2}^{2} g_{2c} \end{bmatrix} \begin{bmatrix} \emptyset_{1} \beta_{11} + \emptyset_{21} \beta_{12} & \emptyset_{11} \beta_{21} + \emptyset_{21} \beta_{22} \\ \emptyset_{12} \beta_{11} + \emptyset_{21} \beta_{12} & \emptyset_{12} \beta_{21} + \emptyset_{22} \beta_{22} \end{bmatrix}$$

$$(2.4-11)$$

where β_{ij} denotes β_{j} for \underline{b}_{i} . [Note that the original A is used in obtaining this result.]

Since all four eigenvalues have been assigned using (2.3-20), $D=D_p$ and the design is complete. If the gain were being designed for only one actuator, the remaining two eigenvalues would have to be assigned by some other means. This is often not easy to do analytically using determinants, and is best done computationally using D', especially for higher order systems.

CHAPTER III

COMPUTATIONAL DESIGN OF FILTER

For systems of order four and greater, the analytic design approach outlined in the previous chapter becomes very cumbersome. The design example was actually a relatively simple case facilitated by the fact that the same types of sensors were used and the filter was designed to detect two events. In most cases, it is not possible to solve for the detection generator explicitly nor is it possible to assign all filter eigenvalues using D_p alone (definitely not for sensor failure events). This chapter will present a design alternative based upon a process called "orthogonal reduction" which is best implemented on a computer. All of these algorithms were first proposed by Beard but also appear in Jones as well.

3.1 Orthogonal Reduction

Many of the processes involved in the filter design involve finding the rank of a matrix or finding a vector in the null-space of a certain matrix. The detection generator, for example, is in the nullspace of M', the detection space of \underline{f} , and the detection order is n-rankM'. The orthogonal reduction procedure is an iterative process which generates a positive semi-definite matrix, the range space of which coincides with the nullspace of a given matrix V, N(V).

Let V be an mxn matrix given by




Fig. 3.1: Flowchart for ORTRED.

$$\bigvee = \begin{bmatrix}
\bigvee_{i}^{\mathsf{T}} \\
\vdots \\
\bigvee_{m}^{\mathsf{T}}
\end{bmatrix}$$
(3.1-1)

where \underline{v}_i^T are the rows of V. Let Ω denote the symmetric matrix whose range space is to coincide with the nullspace of V. Each row of V is then tested to see whether it is orthogonal to the range space of V (the rows of V span $N^{\perp}(V)$) by defining the auxiliary vector

$$\underline{\mathbf{W}}_{i} = \Omega \underline{\mathbf{V}}_{i} \tag{3.1-2}$$

If $\underline{w}_i \neq \underline{0}$, \underline{v}_i is not perpendicular to the columns of Ω (Ω is symmetric) and Ω is reduced so that $\underline{w} = 0$. This is repeated until the columns of Ω , $R(\Omega)$, are all orthogonal to the rows of V, $N^{\perp}(V)$.

The reduction algorithm proceeds as follows:

(i) with Ω i from the previous iteration, form the auxiliary vector

$$\underline{\mathbf{w}}_{i} = \Omega \underline{\mathbf{v}}_{i}$$

(ii) if $\underline{w}_i = \underline{0}$, set

$$\Omega_{i+1} = \Omega_i$$

if $\underline{w}_i \neq \underline{0}$, set

$$\Omega_{i+1} = \Omega_{i} - \frac{\underline{w_{i}}\underline{w_{i}}^{T}}{\underline{w_{i}}^{T}\underline{v_{i}}}$$
(3.1-3)

The procedure must begin with Ω_1 positive definite to ensure Ω remains positive semi-definite and $\underline{\mathbf{w}_i}^T\underline{\mathbf{v}_i} \neq \mathbf{0}$. The rank of

the matrix is equal to the number of reductions performed.

ICODE3 and WL are used when computing the maximal generator. ICODE3 is the row of C associated with the last nonzero auxiliary vector WL. The arrays IQ and WF are used when calculating D'. IQ stores the orders of K associated with the termination points for each row of C, and WF stores the last nonzero auxiliary vector for each row.

3.2 Input failure event design

The computation of D for actuators is accomplished by calling three subroutines: SEPDET, DETGEN, and DGAIN. Subroutine SEPDET first determines whether the events are output separable—it then determines whether the events are mutually detectable.

In the process of determining mutual detectability, SEPDET calls subroutine DETGEN to find the maximal generator for each event. Finally, subroutine DGAIN is called to calculate. Dusing the detection orders and generators from SEPDET. Inputs to the main program FDFIL (see Appendix A) are the system matrix A and its order N, the measurement matrix C and number of sensors NS, the number of actuators NA, the matrix of event vectors FALL and number of events NF, and the filter eigenvalues EV.

3.2.1 Subroutine SEPDET

The flowchart for SEPDET appears in Fig. 3.2. The program first computes μ_i for each f_i according to (2.3-14) and replaces f_i by $A^{\mu}f_i$ in FALL and CF. The rank of CF is found using ORTRED to see whether the events are separable. If not, the error message 'NOT SEPARABLE' is printed and the designer must remove the dependent events from FALL and start again.

Once the events are output separable, the program proceeds to determine whether the events are mutually detectable. The matrix M' in (2.3-24) is generated using C' and K for the full set of events and the rank is found using ORTRED to determine the group detection order, $\mathcal{N}_{G} = N - \mathrm{rankM_F'}$. The call to DETGEN yields the individual detection orders \mathcal{N}_{i} . If $\mathcal{N}_{G} \neq \sum \mathcal{N}_{i}$, the events are not mutually detectable, and one or more events will have to be removed and the process started over.





Fig. 3.2: Flowchart for SEPDET.



3.2.2 Subroutine DETGEN

This routine will calculate the "maximal" generator and detection order $\sqrt[h]{}$ for an event, or alternatively, the "maximum" generator and its order $\sqrt[h]{}_{mod}$ if (C,A) is an unobservable pair. The process is illustrated in Fig. 3.3 and begins with calculating M' in (2.3-24) for the single event and then using ORTRED to find the detection order, $\sqrt[h]{}=N-rankM'$. The resulting nullspace in this case is the detection space of \underline{f} and coincides with the range space of the final Ω .

In addition to being in the detection space of \underline{f} , the detection generator must satisfy (2.3-10). This is accomplished by applying ORTRED to the matrix

$$M_{K} = \left[C \mid CK \mid \cdots \mid CK^{N-1} \right]$$
 (3.1-4)

starting with the final $\Omega_{\rm f}$ from the first step. Since C spans a subspace one dimension greater than C' and the process is started with $\Omega_{\rm f}$ which is orthogonal to C', only one row of C will not be terminated when first encountered. If WL is the last nonzero auxiliary vector for this row $\underline{c}_{\rm j}$, the maximal generator is given by

$$\underline{g} = \left(\frac{\underline{c}_{j}^{T} A^{\mu} \underline{f}}{\underline{c}_{j}^{T} K^{\nu-i} \underline{W}_{1}}\right) \underline{W}_{2}$$
(3.1-5)

As stated earlier, if (C,A) is not observable, the detection generator found in (3.1-5) is not maximal (order is not $\sqrt{}$), but it is the generator of maximum possible order; this





Fig. 3.3: Flowchart for DETGEN.



generator will be referred to as the "modified" generator and has order $V_{\text{mod}} = \text{rank M}_{k}$. If (C,A) is an observable pair, V_{mod} will equal V. The rest of the algorithm computes the vector CK^{k} Af which is one component of the output error for sensor failures.

3.2.3 Subroutine DGAIN

This subroutine will finally compute the detector gain D while assigning the filter eigenvalues. The process begins (see Fig. 3.4) by finding the particular solution of D for

$$DCF = Q_{D} \tag{3.1-5}$$

where

$$Q_{D} = [q_{i}, \dots, q_{NF}]$$

$$q_{D_{i}} = p_{i}q_{i} + \dots + p_{NMOD_{i}} A^{NMOD_{i}-1} q_{i} + A^{NMOD_{i}} q_{i}$$

and $\nu_{\text{mod}_{\underline{i}}}$ and $\underline{g}_{\underline{i}}$ have already been calculated by SEPDET. The coefficients $p_{\underline{i}}$ are found by calling EVAS which computes the coefficients in (2.3-17) generated by $(s-\lambda)^{\nu_{\text{mod}_{\underline{i}}}}$ where λ is the chosen filter eigenvalue (all are same).

If $\Sigma \nu_{\mathrm{mod}_{1}} = \mathrm{n}$, all eigenvalues are assigned and the detector gain is simply D_{p} . Otherwise, the remaining eigenvalues must be assigned using D'. Calculating D' is very similar to the procedure used in calculating D_{p} except that instead of using maximal generators, the last nonzero auxiliary vectors before termination found in reducing M_{F}' are used. Jones refers to this process as "completion of the state space" because one is assigning eigenvalues associated with that portion of the




Fig. 3.4: Flowchart for DGAIN.

state space not covered by a detection space.

Finding D' begins by applying ORTRED to M_F^{\prime} (M' for the full set F) to obtain IQ and WF as explained in section 3.1. D' is then any solution satisfying

$$\mathcal{D}'C'_{=}W=\Psi_{w} \tag{3.1-6}$$

where

$$M = \begin{bmatrix} K_{d_{i-1}} \overline{M}^{\xi_{i}}, \dots, K_{d_{ICP}-1} \end{bmatrix}$$

$$A_{i} \neq 0 \quad i = 1, \dots, NS$$

$$A_{i} \neq 0 \quad i = 1, \dots, NS$$

$$A_{i} \neq 0 \quad i = 1, \dots, NS$$

$$A_{i} \neq 0 \quad i \neq 1, \dots, NS$$

The \underline{w}_{f_i} are the columns of WL corresponding to the rankC' nonzero q_i , and A_F^i , C_F^i correspond to A^i ,C' in (2.3-22) for the full set F. The coefficients p_{ij} are found by calling EVAS for q_i eigenvalues. One solution of (3.1-6) is simply the particular solution

$$D' = \Psi_{w} [(C'_{F}W)^{T}C'_{F}W]^{-1}(C'_{F}W)^{T}$$
(3.1-7)

The general solution for D is found by applying (2.3-21) to the full set F.

3.3 Measurement failure event design

The algorithm for sensor filter design does not use any new subroutines (except SENSOR which calls the routines) but the order and implementation are different. A schematic for the sensor design process is given in Fig. 3.5. SEPDET is called first for (A,C,F) to determine whether the set is




Fig. 3.5: Sensor design process schematic.

mutually detectable (since $C\underline{f}_i = \underline{\hat{e}}_i$, i = 1,...NF, it is automatically separable). If the set is not mutually detectable, events must be removed from F until it is and NF (no. events) set accordingly (F must now be inputted directly into the program instead of being calculated in SENSOR).

DGAIN is now called to calculate A_F^{\prime} (set IAP=1) for use in computing M_F^{\prime} , the observable space of (C',A') (this has been denoted W_0 in the program). The $A\underline{f}_i$ are then generated (recall that \underline{f} is actually $A^{\mu}\underline{f}$ when $\mu \neq 0$) and categorized according to step 3 in Section 2.3.4.2. The \underline{f}_i corresponding to the $A\underline{f}_i$ falling in category (iii) are then removed from F, and the process begins again with the new F and NF until no $A\underline{f}_i$ falls under (iii).

The next step is to call SEPDET for $(A',C',A\underline{f_i})$. If the $A\underline{f_i}$ are not separable, there is no problem since we still have the output error directions $\underline{\hat{e}_i}$ from the events $\underline{f_i}$ to distinguish between sensor failures. Removing the dependent $A\underline{f_i}$ from the set AF_1 we only need make D' a detector gain for this new set AF_2 of NF_2 events. [The program can be easily modified to handle this case by inputting AF_2 and NF_2 into SENSOR and bypassing the statements NF_2 =NF and AF_2 =AF.] If the $A\underline{f_i}$ are not mutually detectable, however, the corresponding $\underline{f_i}$ will have to be removed from F and the whole process restarted with the new F.

Once the $\underline{Af_i}$ are separable/detectable, DGAIN is called to calculate D' (D' is the output D of DGAIN in this case). SEPDET is recalled to regenerate \mathcal{N}_i and $\underline{g_i}$ for the original $\underline{f_i}$ to be used in calculating $\underline{D_p}$. Now DGAIN is called a final time for $(A,C,\underline{f_i})$ with the input D' calculated above to compute D.

CHAPTER IV

APPLICATION TO FLEXIBLE BEAM

In demonstrating various control and failure detection algorithms for large space structures, researchers often use a long beam or rectangular plate as a typical structural element. A beam is usually chosen because of its simplicity and resemblance to a long truss, though plates find their usefulness in simulating the closely spaced frequencies of a flat solar array. In this chapter, the experimental beam at NASA Langley Research Center will be described along with the design of the filter using the finite element description of the beam. The effectiveness of the filter in detecting failures of force actuators on the beam will then be tested using various input frequencies and filter bandwidths in mismatched filter-system models. A position sensor failure will also be simulated for the case where there is only an initial condition on modal amplitudes present. The effect of data sampling will also be investigated.

4.1 NASA LaRC Experimental Beam

In all the failure detection simulation tests, the dynamics model and actuator/sensor types and locations were chosen to correspond to those of the experimental beam at NASA LaRC to predict the performance of the filter in subsequent tests using the actual beam. The Langley beam is made of aluminum (M=0.502 slugs) and is twelve feet long with a 6" x 3/16" cross section (see reference 4). Actuation is provided by electro-




Fig. 4.1: End view of NASA LaRC experimental beam set-up.(taken from reference[4])

TABLE 4.1: Modal frequencies and shapes for first eight modes of LaRC beam (taken from reference[4]).

MODE #	MODAL FREQUENCY (rad/sec)	MODE SHAPE VALUE x=0.5ft x=2.5ft x=6.0ft			
1	0	7.06	6.18	4.64	
2	0	-5.83	-3.15	1.53	
3	11.418	-7.83	-0.60	5.91	
4	31.360	6.45	-4.28	0.00	
5	61.258	5.07	-6.36	6.90	
6	100.900	-3.68	5.31	0.00	
7	150.185	-2.27	1.74	6.84	
8	209.004	-0.88	-2.70	0.00	

magnetic shakers at four discrete locations along the beam, and the horizontal deflections are measured by nine Kaman KD-2300 probes, four of which are colocated with the actuators (see Fig. 4.1). All of the deflections of interest to us will take place in the horizontal plane of the beam.

Because the beam is supported in a gravity field and the actuator dynamics are significant, the experimental beam does not behave exactly as a uniform beam would. Researchers at Langley have therefore found it convenient to perform their structural analysis using a finite element mode. The beam model consists of 24 sections, each of which is constrained so that it can translate and rotate in only one degree of freedom. The SPAR program was then used to obtain the natural frequencies and orthogonal mode shapes for the first ten modes of the beam (see Fig. 4.2a-h for first eight modes). The SPAR generated mode shape values at positions 0.5 ft, 2.5 ft, and 6.0 ft from the end of the beam are given in Table 4.1 for the two rigid body modes (translation and rotation) and first six flex modes along with the modal frequencies.

4.2 State equations for beam model

In order to obtain the modal equations for the beam, we begin with the series expansion for the beam displacement

$$\gamma(\epsilon, t) = \sum_{i=1}^{\infty} \varphi_i(\epsilon) Y_i(t)$$
 (4.2-1)

where $\phi_{\mathbf{i}}(\mathbf{c})$ is an orthogonal set of mode shapes and $\psi_{\mathbf{i}}(\mathbf{t})$ are




Fig. 4.2: SPAR beam modal frequencies and shapes (frequencies in rad/sec). (taken from reference[4])

the modal amplitudes. Next substitute this into the governing differential equation for the undamped beam

$$EI\frac{\partial^4 y}{\partial \xi^4} + m\frac{\partial^2 y}{\partial t^2} = f(\xi, t)$$
 (4.2-2)

where f is the forcing term and m, E, and I are the beam mass (M) per unit length, modulus, and cross-section inertia, respectively. Assuming the use of m point force actuators,

$$f(\xi, \xi) = \sum_{j=1}^{m} S(\xi - \xi_j) u_j(\xi)$$
 (4.2-3)

with ϵ_j being the actuator positions and u_j (t) the control magnitudes, one obtains the set of relations

$$\omega_{i}^{2} \Psi_{i}(t) + \frac{d^{2} \Psi_{i}}{dt^{2}} - \frac{1}{M} \sum_{j=1}^{m} \Phi_{i}(\epsilon_{j}) u_{j}(t) = 0$$
(4.2-4)

where ω_i is the natural frequency of the ith mode and ϕ_i is the normalized mode shape (for ϕ_i not normalized, the input amplitudes must be scaled).

Next, consider casting (4.2-4) in the state-space form

$$\dot{\mathbf{x}} = \mathbf{A} \, \mathbf{x} + \mathbf{B} \, \mathbf{u}$$

$$\dot{\mathbf{y}} = \mathbf{C} \, \mathbf{x}$$
(4.2-5)

where

$$A = \begin{bmatrix} 0 & 1 & & & & \\ -\omega_1^2 & 0 & & & & \\ & -\omega_2^2 & 0 & & & \\ & & & & & \\ & & & & & \\ & & & & & \\ & & & & & \\ & & & & & \\ & & & & & \\ & & & & & \\ & & & & & \\ & & & & \\ & & & & \\ & & & & \\ & & & & \\ & & & & \\ & & & \\ & & & \\ & & & \\ & & & \\ & & & \\ & & & \\ & & & \\ & & & \\$$

$$B = \begin{bmatrix} \frac{1}{M} \phi_{N}(\epsilon_{1}) & \frac{1}{M} \phi_{N}(\epsilon_{2}) & \cdots & \frac{1}{M} \phi_{N}(\epsilon_{m}) \\ \frac{1}{M} \phi_{N}(\epsilon_{1}) & \frac{1}{M} \phi_{N}(\epsilon_{2}) & \cdots & \frac{1}{M} \phi_{N}(\epsilon_{m}) \\ \vdots & \vdots & \vdots & \vdots \\ 0 & 0 & \cdots & \ddots & \vdots \\ \frac{1}{M} \phi_{N}(\epsilon_{1}) & \frac{1}{M} \phi_{N}(\epsilon_{2}) & \cdots & \frac{1}{M} \phi_{N}(\epsilon_{m}) \end{bmatrix}$$

$$C = \begin{bmatrix} \rho_{1}(\alpha_{1}) & 0 & \rho_{2}(\alpha_{1}) & 0 & \cdots & \rho_{N}(\alpha_{1}) \\ \rho_{1}(\alpha_{2}) & 0 & \rho_{2}(\alpha_{2}) & 0 & \cdots & \rho_{N}(\alpha_{2}) \\ \vdots & \vdots & & \vdots & \vdots \\ \rho_{1}(\alpha_{p}) & 0 & \rho_{2}(\alpha_{p}) & 0 & \cdots & \rho_{N}(\alpha_{p}) \end{bmatrix}$$

where the number of modes has been truncated at N, and the use of m force actuators at positions ϵ_j and p translation deflection sensors at positions ϵ_i have been assumed.

4.3 Failure detection filter design for the beam

For all the beam simulations that will appear later

in this chapter, the actuators and sensors located, at 0.5 ft, 2.5 ft, and 6.0 ft from the end of the beam were used. The colocation was chosen simply as a matter of convenience, whereas the sensor located at 9.5 ft was not used since it is not output separable from the one located at 2.5 ft. In order for the state equations (4.2-5) to be a true representation of the beam, normalized mode shapes must be used. Thus, the orthogonal mode shapes in Table 4.1 were normalized according to (L = beam length)

$$\int_{0}^{L} \varphi_{i}^{2}(x) dx = L \qquad (4.3-1)$$

before being used to compute A, B, and C. The orthogonal mode shape values at the actuator locations appear in Table 4.3.

For actuator failure detection, it was always possible to design a filter that could detect a failure of two actuators, but never for all three. This is because the individual detection orders are always two, but the group detection order for the three events is always n (the system order) making the events nonmutually detectable. The events are always output separable since the actuators are not symmetrically opposed with respect to the center of the beam. By extrapolation, it will be possible to detect up to p-l input failure events with a single filter where p is the number of position sensors.

The design for sensor failures was made somewhat more difficult by the fact that when designing for two sensors, it was found that $A\underline{f}_1$ and $A\underline{f}_2$ were not output separable, with

respect to (C',A'). This simply meant that D' only needed to be made a detector gain for either Af_1 or Af_2 and would automatically be a detector gain for the other. The rest of the design proceeded normally resulting in a filter that could detect two failure events. As in the actuator case, it was not possible to detect three sensor events with a single filter.

4.4 Computer simulation of beam

In order to simulate the dynamics of the system and filter, a fifth order Runge-Kutta integration routine was used. The step size was always maintained at a sufficiently small size compared to the period of the highest frequency mode being simulated in order not to misrepresent the continuity of the system dynamics. A listing of the beam simulation program appears in Appendix B.

The program accepts as input the detector gain D calculated by FDFIL and the nominal system (filter) matrix A, actuator effectiveness matrix BF, and measurement matrix CF used in computing D. BS and CS for the system are also initially set equal to the nominal matrices BF and CF, respectively. When the failure time, TFAIL, is reached, the column of BS associated with the failed actuator, or correspondingly, the row of CS associated with the failed sensor, is zeroed out to represent a failure in the off position. The values of BF and CF retain the nominal system values thus creating the driving term in the state error equation.

To easily verify whether the steady-state output error lies in the direction $C\underline{b}_i$ subsequent to the failure of the i^{th} actuator, the output is transformed so that any vector lying in the direction $C\underline{b}_i$ is changed to the direction $\underline{\hat{c}}_{p_i}$. The desired transformation then is

$$\mathcal{R} = \left[(CF)^{\mathsf{T}} (CF)^{\mathsf{T}} \right]^{-1} (CF)^{\mathsf{T}}$$
(4.4-1)

where F is the full matrix of event vectors \underline{b}_i . It is easily verified by direct substitution of (4.4-1) that $RC\underline{b}_i = \frac{\hat{e}}{p_i}$ for i=1,2,3.

Similarly, it would be desirable to transform the output error for the ith sensor event so that an error in the plane spanned by $\hat{\underline{e}}_{p_i}$ and $CK^{\lambda}A\underline{f}_i$ will lie in an easily identifiable plane. Fortunately, the use of three sensors permits a geometrical construction of the desired transformation. Consider the plane spanned by $\hat{\underline{e}}_1$ and $\underline{w} = CK^{\lambda}A\underline{f}_1$ in Fig. 4.3. This is the plane in which the output error is constrained to lie in the event of a sensor #1 failure. Now if the xyz coordinate system is rotated counterclockwise about the x-axis through the angle Υ (the angle that the projection of \underline{w} on the y-z plane makes with the y-axis), the ξ - η plane coincides with the plane spanned by $\hat{\underline{e}}_1$ and \underline{w} . Thus under the transformation

$$\mathcal{R} = \begin{bmatrix} 1 & 0 & 0 \\ 0 & \cos x & \sin x \\ 0 & -\sin x & \cos x \end{bmatrix}$$
 (4.4-2)




Fig. 4.3: Transformation of output error for sensor #1 failures.




Fig. 4.4: Sampled-data system.

an error in the plane spanned by $\frac{\hat{e}}{1}$ and \underline{w} will have a first and second component but no third.

In the next two sections, the effect of model error in the filter and data sampling of the output will be investigated for the deterministic system. These two effects will be of the greatest concern in actual tests of the beam since the filter must necessarily incorporate a truncated model and data processor capability limits the sampling frequency. The effect of actuator, sensor, and plant noise will not be investigated here because they enter the realm of stochastic filter design which is beyond the scope of this work. Even after satisfying the requirements of being a detector gain, there is usually some freedom left in D that can be used to make the behavior of the detection filter approach that of the Kalman filter. Since no attempt was made here to optimize D for noisy systems under the constraints of being a detector gain, results of noise simulations would not reflect the true capabilities of the detection filter.

4.4.1 Effect of model error

Consider the case where the filter model contains fewer modes than the system model—this will always be the case for the actual beam. Let the state and output equations for the system be

$$\begin{bmatrix} \underline{\dot{x}}_{M} \\ \underline{\dot{x}}_{U} \end{bmatrix} = \begin{bmatrix} A_{M} & O \\ O & A_{U} \end{bmatrix} \begin{bmatrix} \underline{\dot{x}}_{M} \\ \underline{\dot{x}}_{U} \end{bmatrix} + \begin{bmatrix} \underline{B}_{M} \\ \underline{B}_{U} \end{bmatrix} \underline{u}$$

$$4 = \begin{bmatrix} C_{M} & C_{U} \end{bmatrix} \begin{bmatrix} \underline{\dot{x}}_{M} \\ \underline{\dot{x}}_{U} \end{bmatrix}$$

$$(4.4-3)$$

and for the filter

$$\hat{\underline{X}}_{M} = A_{M} \hat{\underline{X}}_{M} + B_{M} \underline{U} + D(\underline{Y} - \hat{\underline{Y}})$$

$$\hat{\underline{Y}} = C_{M} \hat{\underline{X}}_{M}$$

$$(4.4-4)$$

where the subscripts M and U denote modeled and unmodeled modes, respectively.

The new state error equations for the modeled modes are

$$\dot{\underline{\mathbf{e}}}_{\mathsf{M}} = (\mathbf{A}_{\mathsf{M}} - \mathbf{D}\mathbf{C}_{\mathsf{M}}) \,\underline{\mathbf{e}}_{\mathsf{M}} - \mathbf{D}\mathbf{C}_{\mathsf{U}}\mathbf{X}_{\mathsf{U}} \tag{4.4-5}$$

and the coupled equations for the system and filter become

$$\begin{bmatrix} \underline{\dot{X}}_{M} \\ \underline{\dot{X}}_{U} \\ \underline{\dot{e}} \end{bmatrix} = \begin{bmatrix} A_{M} & O & O \\ O & A_{U} & O \\ O & -DC_{U} & A_{m}-DC_{M} \end{bmatrix} \begin{bmatrix} \underline{X}_{M} \\ \underline{X}_{U} \\ \underline{e} \end{bmatrix} + \begin{bmatrix} B_{M} \\ B_{U} \\ O \end{bmatrix} \underline{U}$$


$$(4.4-6)$$

The effect of B_u and C_u on the system of (4.4-3) are known as control and observation spillover, respectively. Spillover was first pointed out by Balas (7) in his work on active control of flexible structures. B_u in (4.4-3) has the effect of


driving the unmodeled modes, and $C_{\rm u}$ creates an extra driving term in the state error equation (4.4-5)—however, neither type of spillover can cause filter instability since the triangularity of the dynamics matrix in (4.4-6) is preserved.

The first two simulations performed were for a perfectly matched system and filter (no spillover present) in order to verify the filter design. The detection filter was set up to detect a failure of either actuator #1 at 0.5 ft from the end of the beam, or actuator #2 at 2.5 ft. Results for the simulation of failures of both actuators at 1.0 sec are shown in Fig. 4.5 for a five-mode model and 15 rad/sec filter bandwidth. All three actuators were driving the system with an exponentially decaying sinusoid of the form, $\text{e}^{-0.2\text{t}}\,\sin\omega_{\text{u}}\text{t},$ with an input frequency of $\omega_{\rm u}$ = 20 rad/sec. The three transformed output errors are plotted on the same graph with the nonzero-signal in Fig. 4.5a representing the failure signal corresponding to the direction $\frac{\hat{e}}{1}$ and, in Fig. 4.5b, the direction $\frac{\hat{e}}{2}$. The verification is good to within the number of significant figures in the detector gain used in the simulation.


The effect of model error is dramatically illustrated in Fig. 4.6 for failure of the first actuator. Actuators #1,2,3 were operating at 20, 5, and 50 rad/sec, respectively, and the filter bandwidth was 15 rad/sec. Figure 4.6a is for a four-mode filter model and eight-mode system. The failure signal is not distinguishable from the other signals because



(a) transformed output error for actuator #1 failure.




(b) transformed output error for actuator #2 failure.




(c) real output error for actuator #2 failure.


Figs.4.5a-c: Actuator failure for matched models.



(a) 4-mode filter



(b) 5-mode filter



Figs.4.6a-c: Model error effect for different filter models.

the unmodeled fifth mode with a natural frequency of 61 rad/sec is being excited heavily by the input frequency of 50 rad/sec. This excitation is much less for the five-mode filter of Fig. 4.6b since the mode at 61 rad/sec is now included in the model, and the effect in Fig. 4.6c for the six-mode filter is barely noticeable. Therefore, one should include in his model at least the first mode whose natural frequency lies beyond the highest input frequency.

The results of an eight-mode system/five-mode filter set of tests for various input frequencies and bandwidths are shown in Table 4.2. The peak failure signal for actuator #1 is given along with the peak signal-to-noise ratio—the peak noise is the peak signal achieved in direction $\frac{\hat{e}}{2}$ and $\frac{\hat{e}}{3}$. It appears that for a constant filter bandwidth, the performance of the filter drops off sharply as the input frequency is pushed farther past the filter poles. This is due to faster attenuation of the failure signal than the spillover noise outside the filter bandwidth. For a fixed input frequency, the signal-to-noise ratio reaches a maximum of 45 for a bandwidth of 15 rad/sec and input frequency of 5 rad/sec and a maximum of 36 for a bandwidth of 25 rad/sec and $\omega_u = 20$ rad/sec. Results for three filter bandwidths and three input frequencies are plotted in Figs. 4.7 to 4.9.

It is interesting to note than when the input frequency is being held constant, the trends we are observing are for


TABLE 4.2: Peak failure signals and signal-tonoise ratios for various input frequencies and filter bandwidths in actuator failure tests.


FILTER	INPUT FREQUENCY (rad/sec)						
POLES	5		20		50		
(rad/sec)	*PS	+5/N	PS	S/N	PS	S/N	
5 10 15 20	.0158 .00595 .00297 ^x .00175	41	.00181 .00150 .00119 .000925	4 21 31 35 36	_ .000284 .000255 .000238	- 5 5 5	
25 30	.00114	35 29	.000763		-	-	


^{*}peak failure signal in 1.5-2.0 sec interval +peak failure signal divided by peak noise in other two output directions (1.5-2.0 sec) *xthe corresponding results with the detector gain designed for detecting only actuator#1 failures were: PS=0.00121,S/N=1.5

TABLE 4.3: Normalized mode shape values at sensor and actuator locations (taken from reference[5]).


MODE SHAPE	x=0.5 ft	SHAPE VALUE x=2.5 ft	at x=6.0 ft
.6	1.00	1.00	1.00
φ ₂	-1.59 -1.60	-1.01 -0.123	0.00 1.21
φ_{4}	1.32	-0.876	0.00
φ ₅	1.04 -0.753	-1.30 1.09	1.41
0,	-0.465	0.356	1.40
Ø,	-0.181	-0.553	0.00










Figs.4.7a-c: Actuator tests for λ =-10 rad/sec.






Figs.4.8a-c: Actuator tests for λ =-15 rad/sec.







Figs.4.9a-c: Actuator tests for λ =-20 rad/sec.

constant control spillover—however, the observation spillover coefficient DC $_{\rm u}$ in (4.4-5) changes since D and the filter poles change. But even if the filter poles are held constant and D is changed, the effects can be quite dramatic. For instance, if the detector gain is designed to monitor failures of just actuator #1 instead of both actuators, the signal-to-noise ratios for $\omega_{\rm u}$ = 5 rad/sec between filter poles of 15 and 20 rad/sec are about two rather than 40 to 50. The failure signal itself, however, is relatively unaffected.

A set of simulations was also run for detection of complete failure (zero signal) of the sensor colocated with actuator #1. Instead of driving the system with actuator inputs, initial amplitudes were placed directly on the various modes in order to excite them. Since the output transformation for the sensor case is a pure rotation of coordinate axes, the magnitude of the outputs will actually be in feet if normalized mode shapes are used. Thus, the transformed output errors have physical significance, whereas their meaning was obscured by the transformation in the actuator case.

The results of the sensor failure simulations for filter poles at 15 rad/sec and varying initial conditions are given in Table 4.4 and Fig. 10. In all cases, the two rigid body modes had no initial conditions, and the amplitudes on the first three flex modes were 0.12 ft, 0.09 ft, and 0.06 ft, respectively. The corresponding filter initial conditions

TABLE 4.4: Sensor failure results for filter poles at 15 rad/sec and various initial conditions.


INITIAL		PEAK OUTPUT SIGNALS (ft)				
AMPL	ITUDES γ_{7} .	(ft) % .	+PS ₁	*PS ₂	PN	x _{S/N}
.0045 .0030 .0015 .0003	.0030 .0020 .0010 .0002	.0015 .0010 .0005 .0001	.317 .317 .317 .317 .317	.561 .561 .561 .561	5.92x10-3 3.95x10-3 1.97x10-4 3.13x10-6 5.36x10	95 142 285 1790 ₅


TABLE 4.5: Sensor failure results for various filter bandwidths and fixed initial conditions $(\gamma_{60} = .003 \text{ft}, \gamma_{70} = .002 \text{ft}, \gamma_{80} = .001 \text{ft}).$


FILTER	PEAK (
POLES (rad/sec)	+ _{PS} 1	*PS ₂	PN	× s/N
5 10 15 20 25 30	.781 .491 .316 .224 .177	1.191 .800 .561 .396 .286	.00810 .00456 .00395 .00394 .00288	147 175 142 100 99 74

peak signal in direction #1 (1.5-2.0 sec)
*same for direction #2
same for direction #3


 x_{peak} signal in direction #1 and #2 divided by peak noise in direction #3









Figs.4.10a-c: Sensor tests for various initial conditions.







Figs. 4. lla-c: Sensor tests for various filter bandwidths.

were all zero. The amplitudes on the three unmodeled modes (next three flex modes) are given in the table. The failure signal plane is $\frac{\hat{e}}{2} \times \frac{\hat{e}}{2}$. The model error noise is very sensitive to initial conditions on the unmodeled modes, varying almost proportionally. The failure signal itself though is unaffected.

Table 4.5 shows results when the amplitudes on the three unmodeled modes are held constant at 0.003, 0.002, and 0.001 ft and the filter bandwidth is varied. The signal-to-noise ratio reaches a peak near 10 rad/sec where the attenuation of the spillover noise relative to the failure signal is greatest. Between 25 and 30 rad/sec, there was almost no attenuation of noise whereas there was a 25% reduction in the failure signal resulting in loss of signal-to-noise ratio. Plots for several cases appear in Fig. 4.11.

4.4.2 Sampled-data systems

Instead of monitoring a system continuously, it is usually the case because of computational considerations that sensor data is taken at regular intervals and the output held constant between sampling periods. This scheme is depicted in Fig. 4.4 for the detection filter. The switch at #1 closes once every sampling period to receive an update, and the signal stays constant between sampling times. Switch #2 closes at the same instant switch #1 closes, and

is shown in order to emphasize that the output error to the filter remains constant between sampling updates.

The effect of data sampling on filter performance in detection of actuator #1 failures for filter poles at 15 rad/sec and input frequencies of 20 rad/sec is shown in Table 4.6. As expected, the signal-to-noise ratio increases with sampling rate, but even at 160 hz, it is still a long way from the continuous sampling case where it is 31 (see Table 4.2). As illustrated in Fig. 4.12, the failure signal remains constant for different sampling rates, whereas the noise decreases for faster rates.

As a final illustration of data sampling, consider the case where the sampling rate is held constant at 64 hz, and filter bandwidth is varied. Table 4.7 shows results for filter poles between 5 and 20 rad/sec. At 5 rad/sec, the error signal due to spillover noise reached values nearly equal to the failure signal. Between 10 and 20 rad/sec the signal-to-noise ratio increased as it did for the continuous case. Finally, at 25 rad/sec the filter became unstable because the filter time constants were too fast for the sampled-error feedback to have a stabilizing effect. Plots for several cases appear in Fig. 4.13.

It is important to understand that these data-sampling results are for a case in which the detection filter was designed on a continuous data basis, and then data sampling

TABLE 4.6: Data-sampling results for input frequencies of 20 rad/sec, filter poles at 15 rad/sec, and various sampling rates.

SAMPLING	PEAK OUTPUT ERROR SIGNALS (-10 ⁴)			
FREQUENCY (hz)	⁺ PS	*PN ₂	-PN3	xs/N
50	11.7	3.41	2.21	3.4
64	11.7	2.17	0.70	5.4
96	11.7	1.53	0.43	7.6
160	11.7	1.02	0.25	11.5


Data-sampling results for input frequencies of 20 rad/sec, 64 hz sampling rate, and various filter bandwidths. TABLE 4.7:


FILTER POLES	PEAK OUTPUT	ERROR	SIGNALS (·10 ⁴)	
(rad/sec)	PS	PN_2	PN ₃	S/N
5	17.9	7.49	12.5	1.4
10	14.0	3.53	2.0	4.0
15	11.7	1.53	0.4	5.4
20	9.3	1.35	0.3	6.8


^{*}peak signal in direction #1 (1.5-2.0 sec)
*same for direction #2

⁻same for direction #3


xpeak signal in direction #1 divided by peak
signal in direction #2 and #3 (1.5-2.0 sec)









Figs.4.12a-c: Data sampling tests for various sampling rates(filter bandwidth is 15 rad/sec).



(a) 5 rad/sec



(b) 10 rad/sec



(c) 20 rad/sec

Figs.4.13a-c: Data sampling tests for various filter bandwidths(sampling rate = 64 hz).

was imposed on the resulting filter. It is possible to design the failure detection filter on the basis of a sampled-data description of the dynamics. This protects against the instability observed in these results, but data sampling fundamentally limits the ability of the filter to restrict a continuous failure signature to a single direction or plane in the output space.

CHAPTER V

SUMMARY AND CONCLUSIONS

The failure detection filter performs very well in the context of flexible structure dynamics when the dynamic model in the filter matches that of the system it is monitoring. It was found that the filter usually works quite well even when the description of the system includes modes which are not modeled in the filter. This performance rapidly diminishes, however, as the input frequencies become close to the natural frequencies of the unmodeled modes. For a given input frequency, an optimum filter bandwidth for maximum signal-to-noise ratio usually exists not far beyond the input frequency.

It is not always the case, however, that the filter will perform satisfactorily in the presence of modeling error. Sometimes two different detector gains capable of detecting the same failure event and designed with the same filter poles will yield grossly different detection performances—in one case the signal-to-noise ratio might be 50 and in the other case it might be less by an order of magnitude. This effect is caused by the direct appearance of the detector gain in the filter input due to observation spillover, the same phenomenon encountered when designing control systems for flexible structures.

The filter worked well for sensor failures, even when the initial amplitudes on the unmodeled modes were a significant fraction of those on the modeled modes (up to 7.5% were tested).

By varying filter bandwidth, it was possible to obtain very high signal-to-noise ratios for fixed initial conditions.

As expected, satisfactory performance of the filter designed for continuous data processing when used in a sampled-data mode depended strongly on a very high sampling rate. Only when the sampling rate reached five times the natural frequency of the last system mode did the signal-to-noise ratio surpass 10. As can be anticipated, when the sampling rate to filter bandwidth ratio is too low, the phase lag caused by sampling tended to destabilize the system.

These observations bring to mind several suggestions with regard to both the actual beam experiment and areas for further study:

- (1) To ensure adequate filter performance, it may be necessary to eliminate observation spillover as much as possible—it might be possible to accomplish this using a phase lock loop 10 to comb out only the modeled modes from the output or by reducing the bandwidth of sensor data (one must be careful in doing this, however, not to attenuate the failure signal as well).
- (2) It may be necessary to use a sampling rate of at least 64 hz in order to get stable and adequate performance from the filter—this will depend upon the degree of excitation of the higher modes.
- (3) Even after specifying D to be a detector gain and assign-

ing all the filter eigenvalues, there is still a lot of freedom left in D (especially when D is designed to detect only one event) that could be used to reduce spillover noise—using this freedom would require a more analytic approach to solving for D and involve solving a set of nonlinear simultaneous equations when assigning eigenvalues.

(4) The whole issue of stochastic failure detection filter theory has not even been addressed here—this will be an additional consideration in designing the filter when optimizing signal-to-noise ratios in the presence of plant, actuator, and sensor noise.

APPENDIX A

VM/SP CONVERSATIONAL MONITOR SYSTEM FILE: FDFIL FORTRAN A FDF00020 FDF00030 PROGRAM FDFIL COMPUTES THE DETECTOR GAIN FDF00040 OF THE FAILURE DETECTION FILTER FDF00050 FOR BOTH ACTUATOR AND SENSOR FAILURE EVENTS FDF00060 ************ C* FDF00080 FDF00090 INPUT: N - NUMBER OF SYSTEM STATES FDF00100 NS - NUMBER OF SENSORS FDF00110 NF - NUMBER OF FAILURE EVENTS С IFAL - (=1) TO INPUT EVENT VECTORS FOR SENSOR CASE (=0) THEN CF=I IS GENERATED FOR ALL SENSORS FDF00120 С FDF00130 С FDF00140 IAS - (=1) FOR ACTUATOR EVENTS C FDF00150 (=2) FOR SENSOR EVENTS С FDF00160 EV - FILTER EIGENVALUES FDF00170 A - SYSTEM MATRIX C FDF00180 C - MEASUREMENT MATRIX C FDF00190 FALL - MATRIX OF EVENT VECTORS C FDF00200 (COLUMNS ARE EVENTS) С FDF00210 FDF00220 OUTPUT: D -DETECTOR GAIN FDF00230 DPR - AUXILIARY DETECTOR GAIN FDF00240 MU - ARRAY OF SEPARABILITY ORDERS С FDF00250 NU - ARRAY OF DETECTION ORDERS С FDF00260 NUMOD - ARRAY OF MODIFIED DETECTION ORDERS С IQ - ARRAY OF COMPLETED STATE SPACE ORDERS FDF00270 C FDF00280 CF - MATRIX OF OUTPUT ERROR DIRECTIONS FOR C ACTUATOR FAILURES (COLUMNS ARE VECTORS) FDF00290 C FDF00300 CZKLAF - THIS VECTOR AND THE UNIT VECTOR IN THE C ITH DIRECTION SPAN THE PLANE OF OUTPUT EDE00310 С FDF00320 ERRORS FOR SENSOR FAILURES C FDF00330 C FDF00340 IMSL SUBROUTINES THAT ARE USED: C FDF00350 VMULFM(A,B,C) - C=A(TRANSPOSE)+B C FDF00360 VMULFP(A,B,C) - C=A+B(TRANSPOSE С FDF00370 VMULFF(A,B,C) - C*A*B C FDF00380 LINV1F(A,AI) - AI=A(INVERSE) FDF00390 - EV=EIGENVALUES(A) EIGRF(A.EV) C FDF00400 FDF00420 C FDF00430 С **FDF00440** THIS IS THE MAIN PROGRAM FOR ACTUATOR EVENT FILTER FDF00450 C FDF00460 INTEGER NU(10), ICAT(10) FDF00470 REAL DOUT (20, 10) FDF00480 DOUBLE PRECISION A(20,20),C(10,20),FALL(20,10),CF(10,10),G(20,10). FDF00490 & FDF00500 ZKF(20,20),CPF(10,20),ZMF(200,20),D(20,10), 8 FDF00510 DC(20,20),ADC(20,20),WK(440),REVAL(40),REVEC(800), æ FDF00520 DPR(20, 10), AP(20, 20), EV, EPS, TOL FDF00530 COMPLEX * 16 EVAL(20), EVEC(20,20) FDF00540 EQUIVALENCE(EVAL(1), REVAL(1)), (EVEC(1,1), REVEC(1))

DATA IN, 10/7,8/

FDF00550

```
FDF00560
      READ(IN. 10) N.NS, NF. IFAL, IAS, EV
      READ(IN, 20) ((A(I, J), J=1, 16), I=1, 16),
                                                                            FDF00570
                                                                            FDF00580
                   ((C(I,J),J=1,16),I=1,8),
                                                                            FDF00590
                   ((FALL(I,J),J=1,8),I=1,16)
                                                                            FDF00600
   10 FORMAT(515/E14.4)
                                                                            FDF00610
   20 FORMAT(32(8F10.3/),16(8F10.3/),15(8F10.3/),8F10.3)
                                                                            FDF00620
      WRITE(IO,25) N,NS,NF,IFAL,IAS,EV
   25 FORMAT('N=', I2,5X,'NS=', I2,5X,'NF=', I2,5X,'IFAL=', I2,5X,
                                                                            FDF00630
             'IAS=', I2/'EV=', E14.4/)
                                                                            FDF00640
                                                                            FDF00650
      WRITE(I0,26) ((A(I,J),J=1,8),I=1,8),
                                                                            FDF00660
     8
                    ((C(I,J),J=1,8),I=1,8),
                                                                            FDF00670
                    ((FALL(I,J),J=1.8),I=1.8)
   26 FORMAT(//'A='/8(8F10.4/)//'C='/8(8F10.4/)//'FALL='/8(8F10.4/))
                                                                            FDF00680
                                                                            FDF00690
      IF(IAS.EQ.2) GO TO 27
      CALL SEPDET(A,C,FALL,N,NF,NS,ISEP,IDET,IDIR,C,CF,G,NU,NUMOD,
                                                                            FDF00700
                                                                            FDF00710
                   ZKF, CPF, ZMF)
     &
      IF((ISEP.EQ.1).OR.(IDET.EQ.1)) GO TO 100
                                                                            FDF00720
                                                                            FDF00730
      CALL DGAIN(C,A,EV,G,CF,CPF,NU,NUMOD,N,NF,NS,O,O,DPR,
                                                                            EDE00740
                  ZKF, ZMF, AP, D)
                                                                            FDF00750
      GO TO 28
                                                                            FDF00760
C
                                                                            FDF00770
   CALL THE MAIN PROGRAM FOR SENSOR EVENT FILTER
C*
                                                                            FDF00780
                                                                            FDF00790
   27 CALL SENSOR(C,A,EV,G,NU,CF,CPF,N,NF,NS,
                                                                            FDF00800
                   ZKF, ZMF, FALL, IFAL, IDET, ICAT, D)
                                                                            FDF00810
       DO 271 I=1,10
                                                                            FDF00820
         IF(ICAT(I).EQ.3) STOP
                                                                            FDF00830
       CONTINUE
      IF(IDET.EQ.O) GO TO 28
WRITE(IO,277) IDET,((FALL(I,J),J=1,4),I=1,6)
                                                                            FDF00840
                                                                            FDF00850
                                                                            FDF00860
  277 FORMAT('IDET=', I1//'FALL='/6(4E14.4/)//)
                                                                            FDF00870
      GO TO 200
                                                                            FDF00880
   28 CALL VMULFF(D,C,N,NS,N,20,10,DC,20,IER)
                                                                            FDF00890
      CALL MATSUB(A,DC,20,20,N,N,ADC)
                                                                            FDF00900
          WRITE(I0,29) ((ADC(I,J),J=1,4),I=1,4)
          FORMAT('A-DC='/4(4E14.4/)/)
                                                                            FDF00910
                                                                            FDF00920
    VERIFY THE PLACEMENT OF FILTER EIGENVALUES
      CALL EIGRF (ADC, N, 20, O, REVAL, REVEC, 20, WK, IER)
                                                                            FDF00930
                                                                            FDF00940
      WRITE(IO,30) (EVAL(I), I=1,16)
   30 FORMAT('CLOSED-LOOP EVS ARE: '/16(2F10.4/)/)
                                                                            FDF00950
                                                                            FDF00960
      WRITE(I0.40) ((D(I,J),J=1.3),I=1.16)
   40 FORMAT('GAIN MATRIX D='/16(3E16.6/)//)
                                                                            FDF00970
                                                                            FDF00980
      DO 48 I=1,N
                                                                            FDF00990
        DO 48 J=1,NS
                                                                            FDF01000
          DOUT(I,J)=SNGL(D(I,J))
                                                                            FDF01010
   48 CONTINUE
                                                                            FDF01020
      WRITE(11,50) ((DOUT(I.J), J=1,3), I=1,16)
                                                                            FDF01030
   50 FORMAT(15(3E16.6/),3E16.6)
                                                                            FDF01040
      GO TO 200
                                                                            FDF01050
  100 WRITE(IO, 110) ISEP, IDET
  110 FORMAT ('THE SYSTEM IS NOT SEPARABLE OR DETECTABLE: '/
                                                                            FDF01060
                                                                            FDF01070
              'ISEP=', I1, 10X, 'IDET=', I1)
     &
                                                                            FDF01080
  200 STOP
                                                                            FDF01090
      END
                                                                            FDF01100
C
```

```
FDF01110
    SEPDET DETERMINES SEPARABILITY AND DETECTABILITY OF EVENTS
C*
                                                                            FDF01120
C
      SUBROUTINE SEPDET(A,C,FALL,N,NF,NS,ISEP,IDET,IDIR,CSYS,CF,G,NU,
                                                                            FDF01130
                         NUMOD, ZKF, CPF, ZMF)
                                                                            FDF01140
     &
                                                                            FDF01150
      INTEGER MU(10), NU(10), IQ(10), NUMOD(10)
                                                                            FDF01160
      DOUBLE PRECISION
                 A(20,20),C(10,20),FALL(20,10),CF(10,10),CPF(10,20),
                                                                            FDF01170
                 G(20, 10), ZKF(20, 20), ZMF(200, 20), F(20), CAJ(10, 20).
                                                                            FDF01180
                 CAUF(10), OM(10,10), OMSUB(10,10), WL(20), WF(20,10),
                                                                            FDF01190
     &
                 CFTC(10,20),CFTCF(10,10),CFTCFI(10,10),WKAR(460),
                                                                            FDF01200
                                                                            FDF01210
                 CFTTI(10,20), AFALL(20, 10), AFCF(20,20), CFCF(10,20),
     g,
                 ZMFNUL(20,20),AJ(20,20),ZMFSUB(20,20),FALL2(20,10),
                                                                            FDF01220
                 ZMFSB(10,20), ZMFSB2(10,20), AJ2(20,20), AMUF(20),
                                                                            FDF01230
     &
                                                                            FDF01240
                 CSYS(10,20), EPS, TOL, CAJEPS, ZKNU1
                                                                            FDF01250
      DATA EPS, IO/1.D-4,8/
                                                                            FDF01260
      ISEP=0
                                                                            FDF01270
      IDET=0
                                                                            FDF01280
      DO 3 I=1,N
                                                                            FDF01290
        DO 3 J=1.NF
                                                                            FDF01300
          FALL2(I,J)=FALL(I,J)
                                                                            FDF01310
    3 CONTINUE
                                                                            FDF01320
      DO 20 K=1,NF
                                                                            FDF01330
        DO 5 I=1,N
                                                                            FDF01340
           F(I)=FALL(I,K)
                                                                            FDF01350
        CONTINUE
                                                                            FDF01360
        MU(K)=O
                                                                            FDF01370
        CALL MATID(AJ, 20, N)
                                                                            FDF01380
        CALL VMULFF(C.AJ,NS,N,N,10,20,CAJ,10,IER)
                                                                            FDF01390
         CALL MATVEC(CAJ, F, 10, 20, NS, N, CAJF)
                                                                            FDF01400
         TOL=O.DO
                                                                            FDF01410
        DO 7 I=1,NS
                                                                            FDF01420
           DO 7 J=1.N
                                                                            FDF01430
             CAJEPS=CAJ(I,J)*EPS
                                                                            FDF01440
             TOL=DABS(DMAX1(TOL, CAJEPS))
                                                                            FDF01450
        CONTINUE
                                                                            FDF01460
        NZERO=O
                                                                            FDF01470
         DO 10 I=1.NS
                                                                            FDF01480
           IF(DABS(CAJF(I)).LT.TOL) NZERO*NZERO+1
                                                                            FDF01490
    10
         CONTINUE
                                                                            FDF01500
         IF(NZERO.NE.NS) GO TO 12
                                                                            FDF01510
         MU(K)=MU(K)+1
                                                                            FDF01520
         CALL VMULFF(A,AJ,N,N,N,20,20,AJ2,20,IER)
                                                                            FDF01530
         DO 11 I=1.N
                                                                            FDF01540
           DO 11 J=1,N
                                                                            FDF01550
             AJ(I,J)=AJ2(I,J)
                                                                             FDF01560
    11
         CONTINUE
                                                                            FDF01570
         GO TO 6
                                                                             FDF01580
           WRITE(IO, 13) K,MU(K)
    12
                                                                             FDF01590
           FORMAT('K=', 12,5X,'MU=',12)
    13
                                                                             FDF01600
           CALL MATVEC(AJ, F, 20, 20, N, N, AMUF)
                                                                             FDF01610
         DO 15 I=1,N
                                                                             FDF01620
           FALL(I,K)=AMUF(I)
                                                                             FDF01630
           CF(I,K)=CAJF(I)
                                                                             FDF01640
         CONTINUE
                                                                             FDF01650
    20 CONTINUE
```

```
FDF01660
      WRITE(I0,205) ((CF(I,J),J=1,3),I=1,3)
                                                                               FDF01670
205
      FORMAT('CF='/3(3E16.6/)/)
                                                                               FDF01680
      CALL MATID (OM. 10.NS)
      CALL ORTRED(CF, 10, 10, NS, NF, OM, NS, O, OM, OMSUB,
                                                                               FDF01690
                                                                               FDF01700
                  IRKCF, ICODE3, ZKNU1, WL, IQ, WF)
     Ŗ.
                                                                               FDF01710
      WRITE(IO, 207) IRKCF
                                                                               FDF01720
  207 FORMAT('RANK CF IS ', I2)
                                                                               FDF01730
      IF(IRKCF.EQ.NF) GO TO 21
                                                                               FDF01740
      ISEP=1
                                                                               FDFO1750
      WRITE(ID, 209)
                                                                               FDF01760
      FORMAT ('THE EVENTS ARE NOT SEPARABLE')
209
                                                                               FDF01770
      RETURN
                                                                               FDF01780
   21 CALL VMULFM(CF,C,NS,NF,N,10,10,CFTC,10,IER)
                                                                               FDF01790
      CALL VMULFM(CF, CF, NS, NF, NF, 10, 10, CFTCF, 10, IER)
                                                                               FDF01800
      CALL LINV1F(CFTCF,NF,10,CFTCFI,0,WKAR,IER)
      CALL VMULFF(CFTCFI.CFTC.NF,NF,N,10,10,CFTTI,10,IER)
                                                                               FDF01810
                                                                               FDF01820
      CALL VMULFF(A.FALL,N,N,NF,20,20,AFALL,20,IER)
                                                                               FDF01830
      CALL VMULFF(AFALL, CFTTI, N, NF, N, 20, 10, AFCF, 20, IER)
                                                                               FDF01840
      CALL MATSUB(A, AFCF, 20, 20, N, N, ZKF)
                                                                               FDF01850
      CALL VMULFF(CF, CFTTI, NS, NF, N, 10, 10, CFCF, 10, IER)
                                                                               FDF01860
      CALL MATSUB(C,CFCF, 10, 20, NS, N, CPF)
                                                                               FDF01870
      CALL MATGEN(CPF, ZKF, 10, 20, 200, NS, N, N, ZMFSB, ZMFSB2, ZMF)
                                                                               FDF01880
           WRITE(I0,303) ((ZKF(I,J),J=1,4),I=1,4),
                                                                               FDF01890
                         ((CPF(I,J),J=1,4),I=1,3)
               FORMAT('ZKF='/4(4E14.4/)//'CPF='/3(4E14.4/)//)
                                                                               FDF01900
303
                                                                               FDF01910
      CALL MATID(ZMFNUL, 20, N)
      CALL ORTRED(ZMF, 200, 20, NS*N, N, ZMFNUL, NS, O, ZMFNUL, ZMFSUB,
                                                                               FDF01920
                                                                               FDF01930
                    IRKZMF,ICODE3,ZKNU1,WL,IQ,WF)
     &
      CALL DETGEN(MU, FALL, FALL2, IDIR, CSYS, A, C, N, NS, NF, ZKF, NU, NUMOD, G)
                                                                               EDE01940
                                                                               FDF01950
         WRITE(IO,315) IRKZMF,(NU(I),I=1,2)
                                                                               FDF01960
         FORMAT('IRKZMF=', I2, 10X, 'NU1-2=', 215//)
315
                                                                               FDF01970
       NUG=N-IRKZMF
                                                                               FDFO1980
       INUSUM=0
                                                                               FDF01990
       DO 25 I=1,NF
                                                                               FDF02000
         INUSUM=INUSUM+NU(I)
                                                                               FDF02010
   25 CONTINUE
                                                                               FDF02020
       IF(INUSUM.EQ.NUG) GO TO 30
                                                                               FDF02030
       IDET=1
                                                                               FDF02040
    30 RETURN
                                                                               FDF02050
       END
                                                                               FDF02060
    DETGEN FINDS THE DETECTION ORDER AND GENERATOR FOR THE EVENTS
                                                                               EDE02070
                                                                               FDF02080
       SUBROUTINE DETGEN(MU, FALL, FALL2, IDIR, CSYS, A, C, N, NS, NF, ZKF,
                                                                               FDF02090
                                                                               FDF02100
                          NU, NUMOD, G)
                                                                               FDF02110
       INTEGER MU(10), NU(10), IQ(10), NUMOD(10), LEXP(10)
                                                                               FDF02120
       DOUBLE PRECISION
                                                                               FDF02130
                  FALL(20,10),A(20,20),C(10,20),CSUB(10,20),
      &
                  G(20, 10), F(20), CSF(10), CSFTC(20), CT(20, 10),
                                                                               FDF02140
                                                                               FDF02150
                  ASF(20), ASUB(20,20), ZK(20,20), CP(10,20), ZMP(200,20),
      8
                  ZMK(200,20), ZMKNUL(10,10), CI(20), AMU(20,20),
                                                                               FDF02160
      &
                  WL(20), WF(20, 10), ZKF(20, 20), ZMPNUL(20, 20), ZMKSUB(20, 20), FDF02170
      &
                                                                               FDF02180
                  ZMPSUB(20,20), ZMPSB(10,20), ZMKSB(10,20),
      8
                  ZMPSB2(10,20), ZMKSB2(10,20), AMU2(20,20),
                                                                               FDF02190
      8
                                                                               FDF02200
                  AF(20), FALL2(20, 10), ZKL(20, 20), CZKL(10, 20),
```

```
FDF02210
                 CZKLAF(10), ZKL2(20,20), CSYS(10,20), CZKEPS.
                                                                             FDF02220
                 CFTCF.ZKNU1.CIAMUF.EPS.TOL
                                                                             FDF02230
      DATA IO.EPS/8, 1.D-4/
                                                                             FDF02240
      DO 45 K=1.NF
                                                                             FDF02250
        DO 5 I=1,N
                                                                             FDF02260
          F(I)=FALL(I,K)
                                                                             FDF02270
    5
        CONTINUE
                                                                             FDF02280
        CALL MATVEC(C,F,10,20,NS,N,CSF)
                                                                             FDF02290
        DO 3 I=1,NS
                                                                             FDF02300
          DO 3 J=1,N
             CT(J,I)=C(I,J)
                                                                             FDF02310
                                                                             FDF02320
        CONTINUE
                                                                             FDF02330
        CALL MATVEC(CT.CSF, 20, 10, N, NS, CSFTC)
                                                                             FDF02340
        CFTCF=O.
                                                                             FDF02350
        DO 10 I=1,NS
                                                                             FDF02360
           CFTCF=CFTCF+CSF(I)**2
                                                                             FDF02370
        CONTINUE
   10
                                                                             FDF02380
        DO 15 I=1,N
                                                                             FDF02390
          CSFTC(I)=CSFTC(I)/CFTCF
                                                                             FDF02400
        CONTINUE
                                                                             FDF02410
        CALL MATVEC(A,F,20,20,N,N,ASF)
                                                                             FDF02420
        DO 17 I=1,N
                                                                             FDF02430
           DO 17 J=1.N
                                                                             FDF02440
             ASUB(I,J)=ASF(I)*CSFTC(J)
                                                                             EDE02450
   17
        CONTINUE
                                                                             FDF02460
        DO 18 I=1,NS
                                                                             FDF02470
          DO 18 J=1,N
            CSUB(I,J)=CSF(I)*CSFTC(J)
                                                                             FDF02480
                                                                             FDF02490
   18
        CONTINUE
        CALL MATSUB(A, ASUB, 20, 20, N, N, ZK)
                                                                             FDF02500
                                                                             FDF02510
        CALL MATSUB(C,CSUB, 10, 20, NS, N, CP)
        CALL MATGEN(CP, ZK, 10, 20, 200, NS, N, N, ZMPSB, ZMPSB2, ZMP)
                                                                             FDF02520
                                                                             FDF02530
        CALL MATID(ZMPNUL, 20, N)
        CALL ORTRED(ZMP, 200, 20, NS*N, N, ZMPNUL, NS, O, ZMPNUL, ZMPSUB,
                                                                             FDF02540
                                                                             FDF02550
                     IRKZMP, ICODE3, ZKNU1, WL, IQ, WF)
     &
                                                                             EDE02560
           WRITE(IO, 206) IRKZMP
           FORMAT ('RANK OF ZMP IS ', I2)
                                                                             FDF02570
206
                                                                             FDF02580
        NU(K)=N-IRKZMP
        CALL MATGEN(C,ZK,10,20,200,NS,N,NU(K),ZMKSB,ZMKSB2,ZMK)
                                                                             FDF02590
        CALL ORTRED(ZMK, 200, 20, NS*N, N, ZMPNUL, NS, O, ZMKNUL, ZMKSUB,
                                                                             FDF02600
                     IRKZMK, ICODE3, ZKNU1, WL, IQ, WF)
                                                                             FDF02610
     R.
                                                                             FDF02620
        NUMOD(K)=IRKZMK
                                                                             FDF02630
          WRITE(ID, 216) NUMOD(K)
                                                                             FDF02640
           FORMAT('NUMOD=', I2)
216
                                                                             FDF02650
        DO 20 J=1.N
                                                                             FDF02660
           CI(J)=C(ICODE3,J)
                                                                             FDF02670
        CONTINUE
   20
                                                                             FDF02680
        CIAMUF=0.DO
                                                                             FDF02690
        DO 25 I=1.N
                                                                             FDF02700
           CIAMUF=CIAMUF+CI(I)*F(I)
        CONTINUE
                                                                             FDF02710
   25
                                                                             FDF02720
        DO 40 I=1,N
                                                                             FDF02730
           G(I,K)=(CIAMUF/ZKNU1)*WL(I)
                                                                             FDF02740
        CONTINUE
   40
                                                                             FDF02750
   43
           WRITE(IO, 225) (G(I,K), I=1,4)
```

```
FDF02760
          FORMAT('G='/4E14.4)
225
                                                                            FDF02770
        IF(IDIR.NE.1) GO TO 45
                                                                            FDF02780
        LEXP(K)=0
                                                                            FDF02790
        DO 441 I=1,N
                                                                            FDF02800
           AF(I)=FALL2(I,K)
                                                                            FDF02810
        CONTINUE
  441
                                                                            FDF02820
        CALL MATID(ZKL,20,N)
                                                                            FDF02830
        CALL VMULFF(CSYS,ZKL,NS,N,N,10,20,CZKL,10,IER)
  442
                                                                            FDF02840
        CALL MATVEC(CZKL, AF, 10, 20, NS, N, CZKLAF)
                                                                            FDF02850
        TOL=0.DO
                                                                            FDF02860
        DO 443 I=1.NS
                                                                            FDF02870
           DO 443 J=1,N
                                                                            FDF02880
             CZKEPS=CZKL(I,J)*EPS
                                                                            FDF02890
             TOL=DABS(DMAX1(TOL,CZKEPS))
                                                                            FDF02900
           CONTINUE
  443
                                                                            FDF02910
           NZERO=0
                                                                            FDF02920
           DO 444 I=1.NS
                                                                             FDF02930
             IF(DABS(CZKLAF(I)).LT.TOL) NZERO=NZERO+1
                                                                             FDF02940
           CONTINUE
  444
                                                                             FDF02950
           IF(NZERO.NE.NS) GO TO 446
                                                                             FDF02960
           LEXP(K)=LEXP(K)+1
                                                                             FDF02970
           CALL VMULFF(ZK,ZKL,N,N,N,20,20,ZKL2,20,IER)
                                                                             FDF02980
           DO 445 I=1,N
                                                                             FDF02990
             DO 445 J=1.N
                                                                             FDF03000
               ZKL(I,J)=ZKL2(I,J)
                                                                             FDF03010
           CONTINUE
   445
                                                                             FDF03020
           GO TO 442
                                                                             FDF03030
           WRITE(IO,447) LEXP(K),(CZKLAF(I),I=1,NS)
  446
                                                                             FDF03040
           FORMAT('L=', I2,5X,'CZKLAF=',3E16.6)
   447
                                                                             FDF03050
    45 CONTINUE
                                                                             FDF03060
       RETURN
                                                                             FDF03070
       END
                                                                             FDF03080
С
                                                                             FDF03090
     DGAIN DETERMINES THE DETECTOR GAIN FOR THE FILTER
C*
                                                                             FDF03100
       SUBROUTINE DGAIN(C,A,EV,GEN,CF,CPF,NU,NUMOD,N,NF,NS,IAP,IDPR,DPR, FDF03110
                         ZKF, ZMF, AP, D)
                                                                             FDF03130
       INTEGER NU(10), IQ(10), NUMOD(10)
                                                                             FDF03140
       DOUBLE PRECISION
                  C(10,20),A(20,20),GEN(20,10),CF(10,10),CPF(10,20),
                                                                             FDF03150
      &
                                                                             FDF03160
                  G(20),D(20,10),P(20),Q(20),AJ(20,20),AJG(20),
                                                                             FDF03170
                  QD(20, 10).CFTCF(10, 10).CFTCFI(10, 10).WK(460).
      &
                  CFTTI (10, 10), DP(20, 10), ZMF(200, 20), ZMFNUL(20, 20),
                                                                             FDF03180
      &
                                                                             FDF03190
                  WL(20), WF(20, 10), AP(20, 20), DPC(20, 20), PSI(20),
                  APU(20,20), WFI(20), APUWF(20), PSIW(20,10), ZKF(20,20),
                                                                             FDF03200
                  ZKFQ(20,20), ZKFWF(20), W(20,10), CPFW(10,10), CPFWT(10,10), FDF03210
      &
                  CPFWTI(10,10).CFWTTI(10,10).DPR(20,10).CF2TTI(10,10).
      8
                                                                             FDF03220
      R.
                                                                             FDF03230
                  DPRSUB(20,10),DH(20,10),OMSUB(10,10),AJ2(20,20),
                                                                             FDF03240
                  APJ2(20,20), ZKF02(20,20), ZMFSUB(20,20), EV, EPS, TOL
                                                                             FDF03250
       DATA 10/8/
                                                                             FDF03260
       DO 35 K=1,NF
                                                                             FDF03270
          DO 5 I=1,N
                                                                              FDF03280
            G(I)=GEN(I,K)
                                                                             FDF03290
          CONTINUE
                                                                              FDF03300
          CALL EVAS(20, NUMOD(K), EV,P)
```

```
FDF03310
       DO 10 I=1,N
                                                                           FDF03320
         Q(I)=P(1)*G(I)
                                                                           FDF03330
       CONTINUE
                                                                           FDF03340
       NUMOD 1 = NUMOD (K) - 1
                                                                           FDF03350
       IF(NUMOD1.EQ.O) GO TO 21
                                                                           FDF03360
       DO 20 J=1, NUMOD1
                                                                           FDF03370
         CALL MATPOW(A, 20, N, J, AJ2, AJ)
                                                                           FDF03380
          CALL MATVEC(AJ,G,20,20,N,N,AJG)
                                                                           FDF03390
          DO 15 I=1,N
                                                                           FDF03400
            Q(I)=Q(I)+P(J+1)+AJG(I)
                                                                           FDF03410
          CONTINUE
  15
                                                                           FDF03420
       CONTINUE
  20
                                                                           FDF03430
       CALL MATPOW(A,20,N,NUMOD(K),AJ2,AJ)
  21
                                                                           FDF03440
       CALL MATVEC(AJ,G,20,20,N,N,AJG)
                                                                           FDF03450
       DO 25 I=1,N
                                                                           FDF03460
          Q(I)=Q(I)+AJG(I)
                                                                           FDF03470
        CONTINUE
  25
                                                                           FDF03480
        DO 30 I=1,N
                                                                           FDF03490
          QD(I,K)=Q(I)
                                                                           FDF03500
  30
        CONTINUE
                                                                           FDF03510
  35 CONTINUE
                                                                           FDF03520
      CALL VMULFM(CF,CF,NS,NF,NF,10,10,CFTCF,10,IER)
                                                                           FDF03530
      CALL LINV1F(CFTCF,NF,10,CFTCFI,0,WK,IER)
      CALL VMULFP(CFTCFI,CF,NF,NF,NS,10,10,CFTTI,10,IER)
                                                                           FDF03540
                                                                           FDF03550
      CALL VMULFF(QD,CFTTI,N,NF,NS,20,10,DP,20,IER)
                                                                           FDF03560
      CALL VMULFF(DP,C,N,NS,N,20,10,DPC,20,IER)
                                                                           FDF03570
      CALL MATSUB(A,DPC,20,20,N,N,AP)
                                                                           FDF03580
          WRITE(I0,391) ((DP(I,J),J=1,3),I=1,4),
                                                                           FDF03590
                        ((AP(I,J),J=1,4),I=1,4)
           FORMAT('DP='/4(3E14.4/)//'AP='/4(4E14.4/)/)
                                                                           FDF03600
391
                                                                           FDF03610
      NUSUM=0
                                                                           FDF03620
      DO 40 K=1,NF
                                                                           FDF03630
        NUSUM=NUSUM+NU(K)
                                                                           FDF03640
   40 CONTINUE
                                                                           FDF03650
      IF(IDPR.EQ.1) GO TO 90
                                                                           FDF03660
      IF((N-NUSUM.NE.O).AND.(IAP.NE.1)) GO TO 50
                                                                           FDF03670
      DO 45 I=1.N
                                                                           FDF03680
        DO 45 J=1.NS
                                                                           FDF03690
          D(I,J)=DP(I,J)
                                                                           FDF03700
   45 CONTINUE
                                                                            FDF03710
      RETURN
                                                                            FDF03720
   50 CALL MATID(ZMFNUL, 20, N)
                                                                            FDF03730
      CALL ORTRED(ZMF, 200, 20, NS*N, N, ZMFNUL, NS, 1, ZMFNUL, ZMFSUB,
                                                                            FDF03740
                   IRKZMF, ICODE3, ZKNU1, WL, IQ, WF)
                                                                            FDF03750
           WRITE(IO,411) (IQ(I),I=1,4)
                                                                            FDF03760
          FORMAT('IQ='/4I4)
411
                                                                            FDF03770
      ICP=O
                                                                            FDF03780
      DO 85 I=1,NS
                                                                            FDF03790
         IF(IQ(I).EQ.O) GO TO 85
                                                                            FDF03800
         ICP=ICP+1
                                                                            FDF03810
         CALL EVAS(20, IQ(I), EV,P)
                                                                            FDF03820
         DO 55 L=1,N
                                                                            FDF03830
           WFI(L)=WF(L,I)
                                                                            FDF03840
         CONTINUE
   55
                                                                            FDF03850
         DO 60 J=1,N
```

FILE: FOFIL FORTRAN A

```
FDF03860
          PSI(J)=P(1)+WFI(J)
                                                                            FDF03870
        CONTINUE
                                                                            FDF03880
        IQIM1=IQ(I)-1
                                                                            FDF03890
        IF(IQIM1.EQ.O) GO TO 71
                                                                            FDF03900
        DO 70 J=1, IQIM1
                                                                            FDF03910
          CALL MATPOW(AP, 20, N, J, APJ2, APJ)
                                                                            FDF03920
          CALL MATVEC(APJ, WFI, 20, 20, N, N, APJWF)
                                                                            FDF03930
          DO 65 K=1.N
                                                                            FDF03940
            PSI(K)=PSI(K)+P(J+1)*APJWF(K)
                                                                            FDF03950
          CONTINUE
  65
                                                                            FDF03960
        CONTINUE
  70
                                                                            FDF03970
        CALL MATPOW(AP, 20, N, IQ(I), APJ2, APJ)
  71
                                                                            FDF03980
        CALL MATVEC(APJ, WFI, 20, 20, N, N, APJWF)
                                                                            FDF03990
        DO 75 K=1,N
                                                                            FDF04000
          PSI(K)=PSI(K)+APJWF(K)
                                                                            FDF04010
        CONTINUE
  75
                                                                            FDF04020
        CALL MATPOW(ZKF,20,N,IQ(I)-1,ZKFQ2,ZKFQ)
                                                                            FDF04030
        CALL MATVEC(ZKFQ,WFI,20,20,N,N,ZKFWF)
                                                                            FDF04040
        DO 80 L=1,N
                                                                            FDF04050
          PSIW(L, ICP) *PSI(L)
                                                                            FDF04060
          W(L,ICP)=ZKFWF(L)
                                                                            FDF04070
        CONTINUE
   80
                                                                            FDF04080
   85 CONTINUE
                                                                            FDF04090
      CALL VMULFF(CPF, W, NS, N, ICP, 10, 20, CPFW, 10, IER)
                                                                            FDF04100
      CALL VMULFM(CPFW,CPFW,NS,ICP,ICP,10,10,CPFWT,10,IER)
                                                                            FDF04110
      CALL LINV1F(CPFWT, ICP, 10, CPFWTI, 0, WK, IER)
      CALL VMULFP(CPFWTI, CPFW, ICP, ICP, NS, 10, 10, CFWTTI, 10, IER)
                                                                            FDF04120
                                                                             FDF04130
      CALL VMULFF(PSIW,CFWTTI,N,ICP,NS,20,10,DPR,20,IER)
                                                                             FDF04140
          WRITE(IO,457) ((DPR(I,J),J=1,3),I=1,4)
   90
                                                                             FDF04150
          FORMAT('DPR='/4(3E14.4/)/)
457
                                                                             FDF04160
      CALL VMULFF(CF,CFTTI,NS,NF,NS,10,10,CF2TTI,10,IER)
      CALL VMULFF(DPR.CF2TTI,N,NS,NS,20,10,DPRSUB,20,IER)
                                                                            FDF04170
                                                                             FDF04180
      CALL MATSUB(DPR.DPRSUB, 20, 10, N, NS, DH)
                                                                             FDF04190
      CALL MATADD(DP,DH,20,10,N,NS,D)
                                                                             FDF04200
      RETURN
                                                                             FDF04210
      END
                                                                             FDF04220
                                                                             FDF04230
    SENSOR IS THE MAIN PROGRAM FOR SENSOR EVENT FILTER DESIGN
C*
                                                                             FDF04240
                                                                             FDF04250
      SUBROUTINE SENSOR(C,A,EV,G,NU,CF,CPF,N,NF,NS,
                          ZKF, ZMF, FALL, IFAL, IDET, ICAT, D)
                                                                             FDF04260
                                                                             FDF04270
      INTEGER NU(10), IQ(10), NUMOD(10), ICAT(10)
                                                                             FDF04280
      DOUBLE PRECISION
                 A(20,20),C(10,20),G(20,10),CF(10,10),CPF(10,20),
                                                                             FDF04290
     &
                 ZKF(20,20), ZMF(200,20), FALL(20,10), D(20,10), CCT(10,10), FDF04300
                CCTI(10,10),AP(20,20),WOSUB(10,20),WOSUB2(10,20).
                                                                             FDF04310
     8
                 WO(200,20),F(20),AF(20),WOAF(200),APAF(20),WK(40),
                                                                             FDF04320
     8
                 APAF2(20), CAPAF(10), CAAFN1(10,20), CAFNUL(20,20).
                                                                             FDF04330
                 CAFSUB(20,20), WL(20), WF(20,10), AFALL(20,10),
                                                                             FDF04340
     &
                 DPR(20, 10), CPF2(10, 20), AP2(20, 20), AFALL2(20, 10),
                                                                             FDF04350
                                                                             FDF04360
                 EPS, TOL, WOEPS
                                                                             FDF04370
      DATA 10, EPS/8, 1.D-4/
                                                                             FDF04380
      IDIR=0
                                                                             FDF04390
       IF(IFAL.EQ.1) GO TO 5
                                                                             FDF04400
      CALL VMULFP(C,C,NS,N,NS,10,10,CCT,10,IER)
```

```
FDF04410
     CALL LINV1F(CCT,NS, 10, CCTI,O, WK, IER)
                                                                            FDF04420
      CALL VMULFM(C,CCTI,NS,N,NS,10,10,FALL,20,IER)
                                                                            FDF04430
          WRITE(IO, 121) ((FALL(I,J),J=1.4),I=1.4)
                                                                            FDF04440
          FORMAT('FALL='/4(4E14.4/)//)
   5 CALL SEPDET(A,C,FALL,N,NF,NS,ISEP,IDET,IDIR,C,CF,G,NU,NUMOD,
                                                                            FDF04450
                                                                            FDF04460
                   ZKF, CPF, ZMF)
     &
                                                                            FDF04470
      IF(IDET.EQ.1) RETURN
     CALL DGAIN(C,A,EV,G,CF,CPF,NU,NUMOD,N,NF,NS,1,0,DPR,
                                                                            FDF04480
                                                                            FDF04490
                  ZKF,ZMF,AP,D)
      CALL MATGEN(CPF,AP, 10, 20, 200, NS, N, N, WOSUB, WOSUB2, WO)
                                                                            FDF04500
                                                                            FDF04510
          WRITE(IO, 132) ((WO(I,J),J=1,4),I=1,12)
                                                                            FDF04520
          FORMAT('WO='/12(4E14.4/)//)
132
                                                                            FDF04530
      NSN=NS*N
                                                                            FDF04540
      TOL=O.
                                                                            FDF04550
      DO 10 I=1,NS
                                                                            FDF04560
        DO 10 J=1.N
                                                                            EDE04570
          WOEPS=WO(I,J)*EPS
                                                                            FDF04580
          TOL=DABS(DMAX1(TOL, WOEPS))
                                                                            FDF04590
   10 CONTINUE
                                                                            FDF04600
          WRITE(IO, 143) TOL
                                                                            FDF04610
          FORMAT('TOL=', E14.4/)
143
                                                                            FDF04620
      DO 60 K=1.NF
                                                                            FDF04630
        DO 15 I=1,N
                                                                            FDF04640
          F(I)=FALL(I,K)
                                                                            FDF04650
        CONTINUE
                                                                            FDF04660
        CALL MATVEC(A,F,20,20,N,N,AF)
                                                                            FDF04670
        CALL MATVEC(WO,AF,200,20,NS*N,N,WOAF)
                                                                            FDF04680
           WRITE(IO, 156) (WOAF(I), I=1,8)
                                                                            FDF04690
           FORMAT('WOAF='/2(4E14.4/)//)
156
                                                                            FDF04700
        N0=0
                                                                            FDF04710
        DO 20 I=1,NSN
                                                                            EDE04720
           IF(DABS(WOAF(I)).LT.TOL) NO=NO+1
                                                                            FDF04730
        CONTINUE
   20
                                                                            FDF04740
         IF(NO.EQ.NSN) GO TO 25
                                                                            FDF04750
        ICAT(K)=1
                                                                            FDF04760
         GO TO 60
                                                                            FDF04770
         ICNT=0
   25
                                                                            FDF04780
         DO 30 I=1,N
                                                                            FDF04790
           APAF(I)=AF(I)
                                                                            FDF04800
         CONTINUE
   30
                                                                            FDF04810
         ICNT=ICNT+1
   35
                                                                             FDF04820
         CALL MATVEC(C.APAF, 10, 20, NS, N, CAPAF)
                                                                             FDF04830
         DO 40 I=1,NS
                                                                             FDF04840
           CAAFN1(I,ICNT)=CAPAF(I)
                                                                             FDF04850
   40
         CONTINUE
                                                                             FDF04860
         IF(ICNT.EQ.N) GO TO 50
                                                                             FDFO4870
         CALL MATVEC(AP, APAF, 20, 20, N, N, APAF2)
                                                                             FDF04880
         DO 45 I=1,N
                                                                             FDF04890
           APAF(I)=APAF2(I)
                                                                             FDF04900
    45
         CONTINUE
                                                                             FDF04910
         GO TO 35
                                                                             FDF04920
         CALL MATID(CAFNUL, 20, N)
    50
                                                                             FDF04930
         CALL ORTRED(CAAFN1, NS, N, 10, 20, CAFNUL, NS, O, CAFNUL,
                                                                             FDF04940
                      CAFSUB, IRKCAF, ICODE3, ZKNU1, WL, IQ, WF)
                                                                             FDF04950
         IF(IRKCAF.NE.1) GO TO 55
```

```
FDF04960
        ICAT(K)=2
                                                                            FDF04970
        GO TO 60
                                                                            FDF04980
        ICAT(K)=3
  55
                                                                            FDF04990
   60 CONTINUE
                                                                            FDF05000
          WRITE(IO, 166) (ICAT(K).K=1,4)
                                                                            FDF05010
          FORMAT('ICAT=',413/)
166
                                                                            FDF05020
      DO 65 K=1,NF
                                                                            FDF05030
        IF(ICAT(K).EQ.3) RETURN
                                                                            FDF05040
   65 CONTINUE
                                                                            FDF05050
      CALL VMULFF(A, FALL, N, N, NF, 20, 20, AFALL, 20, IER)
                                                                            FDF05060
          WRITE(IO, 177) ((AFALL(I,J),J=1,4),I=1,6)
                                                                            FDF05070
          FORMAT('AFALL='/6(4E14.4/)//)
177
                                                                            FDF05080
          DO 68 I=1,NS
                                                                            FDF05090
            DO 68 J=1,N
                                                                            FDF05100
              CPF2(I.J)=CPF(I.J)
                                                                            FDF05110
          CONTINUE
   68
                                                                            FDF05120
          DO 69 I=1,N
                                                                            FDF05130
            DO 69 J=1,N
                                                                            FDF05140
              AP2(I,J)=AP(I,J)
                                                                            FDF05150
          CONTINUE
   69
                                                                            FDF05160
      IDIR=1
                                                                            FDF05170
   IF AFALL2 IS INPUTTED TO PROGRAM.
C*
                                                                            FDF05180
    DELETE THESE NEXT 5 STATEMENTS
                                                                            FDF05190
      NF2=NF
                                                                            FDF05200
      DO 70 I=1.N
                                                                            FDF05210
        DO 70 J=1,NF2
                                                                            FDF05220
          AFALL2(I,J)=AFALL(I,J)
                                                                            FDF05230
   70 CONTINUE
                                                                            FDF05240
      CALL SEPDET(AP2,CPF2,AFALL2,N,NF2,NS,ISEP,IDET,IDIR,C,CF,G,
                                                                            FDF05250
                   NU.NUMOD, ZKF, CPF, ZMF)
     R
                                                                            FDF05260
      IF(IDET.EQ.1) RETURN
      CALL DGAIN(CPF2, AP2, EV, G, CF, CPF, NU, NUMOD, N, NF2, NS, O, O, DPR,
                                                                            FDF05270
                                                                            FDF05280
                  ZKF, ZMF, AP, DPR)
                                                                            FDF05290
           WRITE(IO, 127) ((DPR(I,J),J=1,4),I=1,6)
                                                                            FDF05300
           FORMAT('DPR='/6(4E14.4/)//)
127
                                                                            FDF05310
       IDIR=0
                                                                            FDF05320
      CALL SEPDET(A,C,FALL,N,NF,NS,ISEP,IDET,IDIR,C,CF,G,NU,NUMOD,
                                                                            FDF05330
                   ZKF, CPF, ZMF)
     &
      CALL DGAIN(C,A,EV,G,CF,CPF,NU,NUMOD,N,NF,NS,O,1,DPR,
                                                                            FDF05340
                                                                            FDF05350
                  ZKF,ZMF,AP,D)
                                                                            FDF05360
      RETURN
                                                                             FDF05370
       END
                                                                            FDF05380
С
                                                                             FDF05390
    ORTRED PERFORMS ORTHOGONAL REDUCTION ON MATRIX V
C*
                                                                             FDF05400
                                                                             FDF05410
      SUBROUTINE ORTRED(V,M1V,N1V,MV,NV,OMI,NS,ICODE4,OM,OMSUB,
                                                                            FDF05420
                          IRANK, ICODE3, ZKNU1, WL, IQ, WF)
                                                                             FDF05430
      INTEGER IQ(10), ICODE1(10)
                                                                             FDF05440
      DOUBLE PRECISION
                 V(M1V,N1V).OMI(N1V,N1V).OM(N1V,N1V).OMSUB(N1V,N1V).
                                                                             FDF05450
                 VK(20),W(20),WL(20),WF(20,10),WTVK,ZKNU1,EPS,TOL,VKEPS
                                                                            FDF05460
                                                                             FDF05470
      DATA IO, EPS/8, 1.D-4/
                                                                             FDF05480
       ICNT=0
                                                                             FDF05490
       IRANK=0
                                                                             FDF05500
       ICODE2=0
```

VM/SP CONVERSATIONAL MONITOR SYSTEM

FILE: FDFIL FORTRAN A

```
EDE05510
      ICODE3=0
                                                                          FDF05520
          WRITE(10,205)
                                                                          FDF05530
          FORMAT ('ENTERING ORTRED')
205
                                                                          FDF05540
      DO 5 I=1,NS
                                                                          EDE05550
        IQ(I)=0
                                                                          FDF05560
        ICODE1(I)=0
                                                                          FDF05570
    5 CONTINUE
                                                                          FDF05580
      DO 10 I=1,MV
                                                                          FDF05590
        DO 10 J=1,NV
                                                                          FDF05600
          (U,I)IMO=(U,I)MO
                                                                          FDF05610
   10 CONTINUE
                                                                          FDF05620
      DO 95 K=1,MV
                                                                          FDF05630
          TOL=O.
                                                                          FDF05640
        DO 20 J=1,NV
                                                                          FDF05650
          VK(J)=V(K,J)
                                                                          FDF05660
          VKEPS=VK(J)*EPS
                                                                          FDF05670
          TOL=DABS(DMAX1(TOL, VKEPS))
                                                                          FDF05680
        CONTINUE
   20
                                                                          FDF05690
        IF(TOL.LT.EPS) TOL=EPS
                                                                          FDF05700
        ICODE2=ICODE2+1
                                                                          FDF05710
        IARG=ICODE2-((ICODE2-1)/NS)*NS
        IF(ICODE1(IARG).NE.O) GO TO 95
                                                                          FDF05720
                                                                          FDF05730
        CALL MATVEC(OM, VK, N1V, N1V, NV, NV, W)
                                                                          FDF05740
        NZERO=0
                                                                          FDF05750
        DO 25 I=1,NV
                                                                          FDF05760
          IF(DABS(W(I)).LT.TOL) NZERO=NZERO+1
                                                                          FDF05770
   25
        CONTINUE
                                                                          FDF05780
        WTVK=O.
                                                                          FDF05790
        DO 29 I=1,NV
                                                                          FDF05800
          WTVK=WTVK+W(I)*VK(I)
                                                                          FDF05810
   29
        CONTINUE
                                                                          FDF05820
        IF(NZERO.NE.NV) GO TO 28
                                                                          FDF05830
        ICODE1(IARG)=1
                                                                          FDF05840
        GO TO 95
                                                                          FDF05850
        IF(DABS(WTVK).GT.TOL) GO TO 30
   28
                                                                          FDF05860
        ICODE1(IARG)=1
        GO TO 95
                                                                          FDF05870
                                                                           FDF05880
        IF(ICODE3.NE.O) GO TO 35
   30
                                                                          FDF05890
        ICODE3=K
                                                                          FDF05900
   35
        DO. 40 I=1,NV
                                                                          FDF05910
          WL(I)=W(I)
                                                                          FDF05920
   40
        CONTINUE
                                                                          FDF05930
        IF(ICODE4.NE.1) GO TO 80
                                                                          FDF05940
        IQ(IARG)=IQ(IARG)+1
                                                                          FDF05950
        DO 60 I=1.NV
                                                                          FDF05960
          WF(I, IARG)=W(I)
                                                                          FDF05970
        CONTINUE
   60
                                                                          FDF05980
        IRANK=IRANK+1
   80
                                                                          FDF05990
        WTVK=0.
                                                                          FDF06000
        DO 85 I=1,NV
                                                                          FDF06010
          WTVK=WTVK+W(I)*VK(I)
                                                                          FDF06020
   85
        CONTINUE
                                                                          FDF06030
        ZKNU1=WTVK
                                                                          FDF06040
        DO 90 I=1,NV
                                                                          FDF06050
          DO 90 J=1,NV
```

```
FDF06060
            OMSUB(I,J)=W(I)+W(J)/WTVK
                                                                           FDF06070
        CONTINUE
   90
                                                                           FDF06080
        CALL MATSUB(OM, OMSUB, N1V, N1V, NV, NV, OM)
                                                                           FDF06090
   95 CONTINUE
                                                                           FDF06100
      RETURN
                                                                           FDF06110
      END
                                                                           FDF06120
С
                                                                           FDF06130
    MATGEN GENERATES LARGER MATRIX C FROM A AND 8
C*
                                                                           FDFQ6140
      SUBROUTINE MATGEN(A,B,M1A,N1A,M1C,MA,NA,N,CSUB,CSUB2,C)
                                                                           FDF06150
                                                                           FDF06160
      DOUBLE PRECISION A(M1A, N1A), B(N1A, N1A), C(M1C, N1A),
                                                                           FDF06170
                 CSUB(M1A,N1A),CSUB2(M1A,N1A),EPS
                                                                           FDF06180
      DATA EPS/1.D-5/
                                                                           FDF06190
      DO 5 I=1,MA
                                                                            FDF06200
        DO 5 J=1,NA
                                                                            FDF06210
          IF(DABS(A(I,J)).LT.EPS) A(I,J)=0.D0
                                                                            FDF06220
          C(I,J)=A(I,J)
                                                                            FDF06230
          CSUB(I,J)=C(I,J)
                                                                            FDF06240
    5 CONTINUE
                                                                            FDF06250
      IF(N.EQ.1) RETURN
                                                                            FDF06260
      NM1=N-1
                                                                            FDF06270
      DO 15 K=1,NM1
                                                                            FDF06280
        CALL VMULFF(CSUB, B, MA, NA, NA, M1A, N1A, CSUB2, M1A, IER)
                                                                            FDF06290
        DO 10 I=1,MA
                                                                            FDF06300
          DO 10 J=1.NA
                                                                            FDF06310
             CSUB(I,J)=CSUB2(I,J)
                                                                            FDF06320
             C(MA*K+I,J)=CSUB(I,J)
                                                                            FDF06330
        CONTINUE
                                                                            FDF06340
    15 CONTINUE
                                                                            FDF06350
      RETURN
                                                                            FDF06360
      FND
                                                                            FDF06370
C
                                                                            FDF06380
    EVAS DETERMINES COEFFICIENTS P IN CHARACTERISTIC EQUATION
C*
                                                                            FDF06390
                                                                            FDF06400
      SUBROUTINE EVAS(N1,N,EV.P)
                                                                            FDF06410
      REAL POUM(10)
                                                                            FDF06420
      DOUBLE PRECISION P(N1), EV
                                                                            FDF06430
      EVSNGL=SNGL(EV)
                                                                            FDF06440
      DO 5 K=1,N
                                                                            FDF06450
         I=N-K+1
         BETA=(FLOAT(IFACT(N))/(FLOAT(IFACT(N-I))*FLOAT(IFACT(I))))
                                                                            FDF06460
                                                                            FDF06470
              *(EVSNGL**I)
                                                                            FDF06480
         PDUM(K)=((-1.0)**I)*BETA
                                                                            FDF06490
         P(K)=DBLE(PDUM(K))
                                                                            FDF06500
     5 CONTINUE
                                                                            FDF06510
       RETURN
                                                                            FDF06520
       END
                                                                            FDF06530
С
                                                                            FDF06540
    MULTIPLIES MATRIX BY VECTOR
C*
                                                                            FDF06550
С
                                                                            FDF06560
       SUBROUTINE MATVEC(ARRAY, V, M1, N1, M, N, RET)
                                                                            FDF06570
       DOUBLE PRECISION ARRAY(M1,N1),V(N1),RET(M1)
                                                                            FDF06580
       DO 10 I=1.M
                                                                            FDF06590
         RET(I)=0.DO
                                                                            FDF06600
         DO 10 J=1,N
```

FILE: FDFIL FORTRAN A

```
FDF06610
          RET(I)=RET(I)+ARRAY(I,J)*V(J)
                                                                           FDF06620
   10 CONTINUE
                                                                           FDF06630
      RETURN
                                                                           FDF06640
      END
                                                                           FDF06650
С
                                                                           FDF06660
C+
    ADDS MATRIX B TO MATRIX A
                                                                           FDF06670
                                                                           FDF06680
      SUBROUTINE MATADD(A.B.M1,N1,M.N.RET)
                                                                           FDF06690
      DOUBLE PRECISION A(M1,N1),B(M1,N1),RET(M1,N1)
                                                                           FDF06700
      DO 10 I=1,M
                                                                           FDF06710
        DO 10 J=1.N
                                                                           FDF06720
          RET(I,J)=A(I,J)+B(I,J)
                                                                           FDF06730
   10 CONTINUE
                                                                           FDF06740
      RETURN
                                                                           FDF06750
      FND
                                                                           FDF06760
C
                                                                           FDF06770
    SUBTRACTS MATRIX B FROM A
C*
                                                                           FDF06780
                                                                           FDF06790
      SUBROUTINE MATSUB(A,B,M1,N1,M,N,RET)
                                                                           FDF06800
      DOUBLE PRECISION A(M1,N1),B(M1,N1),RET(M1,N1)
                                                                           FDF06810
      DO 10 I=1,M
                                                                           FDF06820
        DO 10 J=1,N
                                                                           FDF06830
          RET(I,J)=A(I,J)-B(I,J)
                                                                           FDF06840
    10 CONTINUE
                                                                           FDF06850
      RETURN
                                                                           FDF06860
      END
                                                                           FDF06870
                                                                           FDF06880
    GENERATES THE IDENTITY MATRIX
C*
                                                                           FDF06890
                                                                           FDF06900
       SUBROUTINE MATID(A,N1,N)
                                                                           FDF06910
      DOUBLE PRECISION A(N1,N1)
                                                                           EDE06920
      DO 20 I=1.N
                                                                           FDF06930
         DO 10 J=1,N
                                                                           FDF06940
           A(I,J)=0.D0
                                                                           FDF06950
    10
         CONTINUE
                                                                           FDF06960
         A(I,I)=1.000
                                                                           FDF06970
    20 CONTINUE
                                                                           FDF06980
       RETURN
                                                                           FDF06990
       END
                                                                           FDF07000
С
                                                                           FDF07010
    RAISES MATRIX & TO POWER K
C*
                                                                           FDF07020
                                                                           FDF07030
       SUBROUTINE MATPOW(A,N1,N,K,AK2,AK)
                                                                           FDF07040
       DOUBLE PRECISION A(N1,N1),AK(N1,N1),AK2(N1,N1)
                                                                           FDF07050
       CALL MATID(AK,N1,N)
                                                                           FDF07060
       IF(K.EQ.O) RETURN
                                                                           FDF07070
       DO 10 IDUM=1.K
                                                                           FDF07080
         CALL VMULFF(A,AK,N,N,N,N1,N1,AK2,N1,IER)
                                                                           FDF07090
         DO 5 I=1,N
                                                                           FDF07100
           DO 3 J=1,N
                                                                           FDF07110
             AK(I,J)=AK2(I,J)
                                                                           FDF07120
         CONTINUE
                                                                           FDF07130
    10 CONTINUE
                                                                           FDF07140
       RETURN
                                                                           FDF07150
       END
```

VM/SP CONVERSATIONAL MONITOR SYSTEM

C C* C	FINDS FACTORIAL OF N INTEGER FUNCTION IFACT(N) IFACT=1 IF(N.LE.1) RETURN DD 10 J=2,N IFACT=IFACT+J 10 CONTINUE	FDF07160 FDF07170 FDF07180 FDF07190 FDF07200 FDF07210 FDF07230 FDF07230 FDF07250
	RETURN	FDF07250 FDF07260
	END	

FILE: FDFIL FORTRAN A

++++++++++++++ ++++++++++++++ I---MASSACHUSETTS INSTITUTE OF TECHNOLOGY---I ------III III III

٥.

٥.

٥.

ο.

Ο.

٥.

٥.

٥.

Ο.

٥.

Ο. ٥.

ο. ٥.

ο. ٥.

0.

o. o.

0. 0.

0. 0.

0.

Ο. ٥.

٥.

٥.

-43683. 1.321 -0.181

-0.876 -0.553 0.00 0.00

-983.45 Ο.

٥.

٥.

٥.

ο.

0.

ο.

0.

٥.

٥.

Ο.

ο.

0. 1.0

Ο. ٥.

Ο. ٥.

Ο.

٥. ٥.

٥. ٥.

ο. ٥.

٥. Ο. Ο.

٥.

0. 1.0

Ο.

٥. ٥. ٥.

ο. 0. ٥. ٥.

FILE. IDI		•				
0. 0. 0. 0. 0. 0. 0. 0. 0. 0. 0. 0. 0. 0	3 3 15.0EO 1.0 0. 0. 0. 0. 0. 0. 0. 0. 0. 0. 0. 0. 0	0 1 0. 0. 0. 0. 0. 0. 0. 0. 0. 0. 0. 0. 0. 0	0.0.000.0000000000000000000000000000000	0. 0. 0. 0. 0. 0. 0. 0. 0. 0. 0. 0. 0. 0	0.0000000000000000000000000000000000000	
0. 0. 0. 1.992 0. -3.167 0. -3.187 0. 2.631 0. 2.072 0. -1.500 0. -0.9263 0. -0.3606	0. 1.992 0. -2.012 0. -0.2450 0. -1.745 0. -2.590 0. 2.171 0. 0.7092 0. -1.102	0. 1.992 0. 0.000 0. 2.410 0. 0.000 0. 2.809 0. 0.000 0. 2.789 0.				

DATA

FILE: FDFIL

APPENDIX B

FILE: FDSIM FORTRAN A VM/SP CONVERSATIONAL MONITOR SYSTEM

```
FDS00020
                                                                   FDS00030
               PROGRAM FDSIM SIMULATES CONTINUOUS
                                                                   FDS00040
                   SYSTEM AND FILTER DYNAMICS
                                                                   FDS00050
             FOR FAILURE DETECTION AND IDENTIFICATION
                                                                   FDS00060
FDS00090
  INPUT: NSYS - NUMBER OF SYSTEM STATES
                                                                   FDS00100
          NFIL - NUMBER OF FILTER STATES
                                                                   FDS00110
          NS - NUMBER OF SENSORS
C
                                                                   FDS00120
          NA - NUMBER OF ACTUATORS
                                                                   FDS00130
          NF - NUMBER OF FAILURE EVENTS
                                                                   FDS00140
          IAS - (=1) FOR ACTUATOR FAILURES
                                                                   FDS00150
               (=2) FOR SENSOR FAILURES
                                                                   FDS00160
          OMU - ACTUATOR INPUT FREQUENCY
C
                                                                   FDS00170
          ISR - SAMPLING RATE (HZ)
                                                                   FDS00180
          NTSEC - INTEGRATION FREQUENCY (HZ)
                                                                   FDS00190
          IFAIL - # OF FAILED ACTUATOR OR SENSOR
                                                                   FDS00200
          TFAIL - TIME OF FAILURE (SEC)
                                                                   FDS00210
          TLAST - TIME OF SIMULATION
C
                                                                   FDS00220
          A - SYSTEM MATRIX
          BS - CONTROL EFFECTIVENESS MATRIX FOR SYSTEM
                                                                   FDS00230
С
                                                                 - FDS00240
          CS - MEASUREMENT MATRIX FOR SYSTEM
          CF1 - MATRIX OF OUTPUT ERROR DIRECTIONS FOR
                                                                   FDS00250
                ACTUATOR FAILURES (COLUMNS ARE VECTORS)
                                                                   FDS00260
C
                                                                   FDS00270
          D - DETECTOR GAIN
                                                                   FDS00280
          X - INITIAL STATES
                                                                   FDS00290
                                                                   FDS00300
   OUTPUT: RE - TRANSFORMED OUTPUT ERROR VECTOR
C*******************************
                                                           ********FDS00320
C
                                                                    FDS00340
C
      DIMENSION A(20,20),BS(20,10),BF(20,10),CS(10,20),U(10),
                                                                    FDS00350
               D(20, 10), CF1(10, 10), X(40), XDOT(40), E(10), S(10, 10),
                                                                    FDS00360
               R(10,10),CFTCF(10,10),CFTCFI(10,10),CFTTI(10,10),
                                                                    FDS00370
     R
                                                                    FDS00380
               WK(40), WK1(40,9), RE(10), C1A(24), CF(10,20),
     &
                                                                    FDS00390
               XS(20),XF(20),YS(10),YF(10),
     &
                                                                    FDS00400
                TIME(5000), RE1(5000), RE2(5000), RE3(5000)
                                                                    FDS00410
      EXTERNAL FCN
      DATA IN, IO, IND, TOL, EPS, NW/9, 10, 1, 0.001, 1.E-4,40/
                                                                    FDS00420
                                                                    FDS00430
      COMMON A.BS.BF.CS.CF.D.E.U.OMU.NSYS.NFIL.NA.NS
                                                                    FDS00440
      CALL PLOTS(IDUM, IDUM, 18)
      READ(IN,5) NSYS,NFIL,NS,NA,NF,IAS,OMU,ISR,NTSEC,IFAIL,TFAIL,TLAST,FDS00450
                 ((A(I,J),J=1,16),I=1,16),
                                                                    FDS00470
                 ((BS(I,J),J=1,8),I=1,16),
     R.
                                                                    FDS00480
                 ((CS(I,J),J=1,16),I=1,8),
     &
                                                                    FDS00490
                 ((CF1(I,J),J=1,3),I=1,8),
     &
                                                                    FDS00500
                 ((D(I,J),J=1,3),I=1,16),
     R
                                                                    FDS00510
                 (X(I),I=1,32)
     5 FORMAT(613/F10.4/13/213,2F10.4/32(8F10.4/),16(8F10.4/),
                                                                   FDS00520
     & 16(8F10.4/),8(3E16.6/),16(3E16.6/),4(8F10.4/))
                                                                    FDS00530
      WRITE(10.7) NSYS, NFIL, NS, NA, NF, NTSEC, IFAIL, TFAIL, TLAST,
                                                                    FDS00540
                                                                    FDS00550
                  ((CF1(I,J),J=1,4),I=1,4),
```

```
& ((D(I,J),J=1,4),I=1,4) FDS00560
7 FORMAT('NSYS=',I2,'NFIL=',I2,5X,'NS=',I2,5X,'NA=',I2,5X,'NF=',I2/FDS00570
& 'NTSEC=',I3,5X,'IFAIL=',I2,5X,'TFAIL=',F8.3,5X,'TLAST=', FDS00580
             F8.3/'CF1='/4(4E14.4/)/'D='/4(4E14.4/)/)
    8
                                                                              FDS00600
     NE = NSYS+NFIL
                                                                              FDS00610
     DO 10 I=1,NFIL
                                                                              FDS00620
       DO 10 J=1,NA
                                                                              FDS00630
         BF(I,J)*BS(I,J)
                                                                              FDS00640
  10 CONTINUE
                                                                              FDS00650
     DO 12 I=1,NS
                                                                              FDS00660
       DO 12 J=1,NFIL
                                                                              FDS00670
         CF(I,J)=CS(I,J)
                                                                              FDS00680
  12 CONTINUE
                                                                              FDS00690
     DO 20 I=1.NS
                                                                              FDS00700
       DO 15 J=1.NF
                                                                              FDS00710
          S(I,J)=0.
                                                                              FDS00720
       CONTINUE
  15
                                                                              FDS00730
       S(I,I)=1.0
                                                                              FDS00740
  20 CONTINUE
                                                                              FDS00750
     IF(IAS.EQ.2) GO TO 21
     CALL VMULFM(CF1,CF1,NS,NF,NF,10,10,CFTCF,10,IER)
                                                                               FDS00760
                                                                              FDS00770
     CALL LINV1F(CFTCF,NF,10,CFTCFI,0,WK,IER)
     CALL VMULFP(CFTCFI, CF1, NF, NF, NS, 10, 10, CFTTI, 10, IER)
                                                                               FDS00780
                                                                              FDS00790
     CALL VMULFF(S,CFTTI,NS,NF,NS,10,10,R,10,IER)
                                                                               FDS00800
      GO TO 24
                                                                               FDS00810
  21 CDSGAM=CF1(2,1)/SQRT(CF1(2,1)**2+CF1(3,1)**2)
                                                                               FDS00820
      SINGAM=CF1(3,1)/SQRT(CF1(2,1)**2+CF1(3,1)**2)
                                                                               FDS00830
      R(1,1)=1.0
                                                                               FDS00840
      R(1,2)=0.
                                                                               FDS00850
      R(1,3)=0.
                                                                               FDS00860
      R(2,1)=0.
                                                                               FDS00870
      R(2,2)=COSGAM
                                                                               FDS00880
      R(2,3)=SINGAM
                                                                               FDS00890
      R(3,1)=0.
                                                                               FDS00900
      R(3,2) = - SINGAM
                                                                               FDS00910
      R(3,3)=COSGAM
                                                                               FDS00920
   24 T=O.
                                                                               FDS00930
      CALL FCN(NE,T,X,XDOT)
                                                                               FDS00940
      WRITE(10,25)
   25 FORMAT(2X, 'TIME', 16X, 'E1', 12X, 'E2', 12X, 'E3'/)
                                                                               FDS00950
                                                                               FDS00960
      WRITE(10.30) T,(RE(1),1=1,3)
                                                                               FDS00970
   30 FORMAT(2X,F6.3,10X,3E14.4)
                                                                               FDS00980
      ILAST=INT(TLAST)+NTSEC
                                                                               FDS00990
      IPLOT=ILAST
                                                                               FDS01000
      NFE=NTSEC/ISR
                                                                               FDS01010
      INDEXE=0
                                                                               FDS01020
      IWRT=0
                                                                               FDS01030
      DO 50 K=1, ILAST
                                                                               FDS01040
        TEND=FLOAT(K)/FLOAT(NTSEC)
                                                                               FDS01050
    NEXT STATEMENTS FOR DATA-SAMPLING ONLY
C+
                                                                               FDS01060
        INDEXE=INDEXE+1
C
                                                                               FDS01070
         IF(INDEXE.NE.NFE) GO TO 38
С
                                                                               FDS01080
         NP1=NSYS+1
С
                                                                               FDS01090
         DO 32 I=1,NSYS
C
                                                                               FDS01100
           XS(I)=X(I)
```

```
FDS01110
C
   32
        CONTINUE
                                                                               FDS01120
         DO 34 I=NP1,NE
                                                                              FDS01130
C
           XF(I-NSYS)=X(I)
                                                                               FDS01140
С
         CONTINUE
                                                                              FDS01150
C
   34
         CALL MATVEC(CS, XS, 10, 20, NS, NSYS, YS)
С
                                                                               FDS01160
         CALL MATVEC(CF, XF, 10, 20, NS, NFIL, YF)
                                                                               FDS01170
C
         CALL VECS(YS, YF, 10, NS, E)
C
                                                                               FDS01180
         INDEXE=0
                                                                               FDS01190
C
         IF(T.LT.TFAIL) GO TO 41 IF(IFLAG.EQ.1) GO TO 41
                                                                               FDS01200
   38
                                                                               FDS01210
         TFLAG=1
                                                                               FDS01220
         IF(IAS.EQ.2) GO TO 415
                                                                               FDS01230
         DO 40 I=1.NSYS
                                                                               FDS01240
           BS(I.IFAIL)=O.
                                                                               FDS01250
         CONTINUE
   40
                                                                               FDSQ1260
         GO TO 41
                                                                               FDS01270
         DO 416 J=1,NSYS
   415
                                                                               EDS01280
           CS(IFAIL, J)=O.
                                                                               FDS01290
         CONTINUE
                                                                               FDS01300
   416
         CALL DVERK(NE, FCN, T, X, TEND, TOL, IND, C1A, NW, WK1, IER)
    41
                                                                               FDS01310
         IF(IND.LT.O .OR. IER.GT.O) GO TO 62
                                                                               FDS01320
         CALL MATVEC(R.E. 10, 10, NS, NS, RE)
                                                                               FDS01330
         TIME(K)=T
                                                                               FDS01340
         RE1(K)=RE(1)
                                                                               FDS01350
         RE2(K)=RE(2)
                                                                               FDS01360
         RE3(K)=RE(3).
                                                                               FDS01370
          IWRT=IWRT+1
                                                                               FDS01380
          IF(IWRT.NE.5) GO TO 50
                                                                                FDS01390
          WRITE(IO,45) T.(RE(I),I=1,3)
                                                                                FDS01400
         FORMAT(2X, F6.3, 10X, 3E14.4)
    45
                                                                                FDS01410
                                                                                FDS01420
    50 CONTINUE
                                                                                FDS01430
       CALL PICTUR(8.0,3.0,'TIME(SEC)',9,'ERROR(FT)',9,
                                                                                FDS01440
                     TIME, RE1, IPLOT, O., O,
      &
                                                                                FDS01450
                     TIME, RE2, IPLOT, O., 1,
                                                                                FDS01460
      8
                     TIME.RE3, IPLOT, O., 2)
                                                                                FDS01470
        CALL ENDPLT(12.0,0.0,999)
                                                                                FDS01480
        GO TO 100
                                                                                FDS01490
    62 WRITE(10,75)
                                                                                FDS01500
    75 FORMAT('IND<O OR IER>O')
                                                                                FDS01510
    100 STOP
                                                                                FDS01520
        END
                                                                                FDS01530
                                                                                FDS01540
 C
 С
                                                                                FDS01550
 C
                                                                                FD$01560
        SUBROUTINE FCN(NE,T,X,XDOT)
        DIMENSION X(NE), XDOT(NE), U(10), BS(20, 10), BF(20, 10), CS(10, 20),
                                                                                FDS01570
                   XS(20), XSDOT(20), XF(20), XFDOT(20), YS(10), YF(10),
                                                                                FDS01580
       &
                   E(10),D(20,10),A(20,20),AXS(20),AXF(20),BSU(20),
                                                                                FDS01590
       &
                   BFU(20),DE(20),AXFBFU(20),CF(10,20)
                                                                                FDS01600
                                                                                FDS01610
       &
        COMMON A.BS.BF.CS.CF.D.E.U.OMU.NSYS.NFIL.NA.NS
                                                                                FDS01620
        U(1) = EXP(-0.2 * T) * SIN(OMU * T)
                                                                                FDS01630
        U(2)=EXP(-0.2*T)*SIN(OMU*T)
                                                                                FDS01640
        U(3)=EXP(-0.2*T)+SIN(OMU*T)
                                                                                FDS01650
        NP 1=NSYS+1
```

```
FDS01660
      DO 5 I=1,NSYS
                                                                             FDS01670
        XS(I)=X(I)
                                                                             FDS01680
        XSDOT(I)=XDOT(I)
                                                                             FDS01690
    5 CONTINUE
                                                                             FDS01700
      DO 10 I=NP1,NE
                                                                             FDS01710
        XF(I-NSYS)=X(I)
                                                                             FDS01720
        XFDOT(I-NSYS)=XDOT(I)
                                                                             FDS01730
   10 CONTINUE
                                                                             FDS01740
      CALL MATVEC(A,XS,20,20,NSYS,NSYS,AXS)
                                                                             FDS01750
      CALL MATVEC(BS.U.20, 10, NSYS, NA, BSU)
                                                                             FDS01760
      CALL VECP(AXS, BSU, 20, NSYS, XSDOT)
                                                                             FDS01770
      CALL MATVEC(A,XF,20,20,NFIL,NFIL,AXF)
                                                                             FDS01780
      CALL MATVEC(CS, XS, 10, 20, NS, NSYS, YS)
                                                                             FDS01790
      CALL MATVEC(CF, XF, 10, 20, NS, NFIL, YF)
                                                                             FDS01800
      CALL VECS(YS.YF. 10, NS, E)
                                                                             FDS01810
      CALL MATVEC(D.E.20, 10, NFIL.NS, DE)
                                                                             FDS01820
      CALL MATVEC(BF.U.20, 10, NFIL, NA, BFU)
                                                                             FDS01830
      CALL VECP(AXF, BFU, 20, NFIL, AXFBFU)
                                                                             FDS01840
      CALL VECP(AXFBFU, DE, 20, NFIL, XFDOT)
                                                                             FDS01850
      DO 15 I=1,NSYS
                                                                             FDS01860
        XDOT(I)=XSDOT(I)
                                                                             FDS01870
   15 CONTINUE
                                                                             FDS01880
      DO 20 I=NP1,NE
                                                                             FDS01890
        XDOT(I)=XFDOT(I-NSYS)
                                                                             FDS01900
   20 CONTINUE
                                                                             FDS01910
      RETURN
                                                                             FDS01920
      END
                                                                             FDS01930
C
                                                                             FDS01940
С
                                                                             FDS01950
                                                                             FDS01960
      SUBROUTINE MATVEC(ARRAY, V.M1, N1, M, N, RET)
                                                                             FDS01970
      DIMENSION ARRAY(M1,N1),V(N1),RET(M1)
                                                                             FDS01980
      DO 10 I=1,M
                                                                             FDS01990
        RET(I)=0.
                                                                             FDS02000
        DO 10 J=1.N
                                                                             FDS02010
           RET(I)=RET(I)+ARRAY(I,J)*V(J)
                                                                             FDS02020
   10 CONTINUE
                                                                             FDS02030
      RETURN
                                                                             FDS02040
      END
                                                                             FDS02050
C
                                                                             FDS02060
С
                                                                             FDS02070
C
                                                                             FDS02080
      SUBROUTINE VECP(V1, V2, N1, N, VADD)
                                                                             FDS02090
      DIMENSION V1(N1), V2(N1), VADD(N1)
                                                                             FDS02100
      DO 5 I=1,N
                                                                             FDS02110
         VADD(I)=V1(I)+V2(I)
                                                                             FDS02120
    5 CONTINUE
                                                                             FDS02130
      RETURN
                                                                             FDS02140
      END
                                                                             FDS02150
C
                                                                             FDS02160
C
                                                                             FDS02170
                                                                             FDS02180
       SUBROUTINE VECS(V1, V2, N1, N, VSUB)
                                                                             FDS02190
      DIMENSION V1(N1), V2(N1), VSUB(N1)
                                                                             FDS02200
      DO 5 I=1,N
VSUB(I)=V1(I)-V2(I)
                                                                             FDS02210
                                                                             FDS02220
     5 CONTINUE
                                                                             FDS02230
       RETURN
                                                                             FDS02240
       END
```

Ο.

ο.

ο.

1.00

1.04

-1.59

-0.753

-1.01

Ο.

Ο.

Ο.

٥.

ο.

0.

-1.60

-0.465

-0.123

1.321

-0.181

-0.876

0.

ο.

0.

```
VM/SP CONVERSATIONAL MONITOR SYSTEM
                          A
FILE: FDSIMS
                DATA
                                                      ٥.
                                                                 -0.553
                                                                           ο.
                                           0.356
-1.30
           ο.
                      1.09
                                ο.
                                                                 0.00
                                                                           ٥.
                     0.00
                                0.
                                           1.21
                                                      ο.
          ٥.
1.00
                                                      ٥.
                                                                 0.00
                                                                           Ο.
                                           1.40
                                ο.
1.41
           ο.
                     0.00
Ο.
Ο.
0.
٥.
ο.
ο.
0.
٥.
٥.
0.
    O.177572E+02
                     0.584335E+00
                                       Q. 105736E+01
                                      -0.195613E+01
                      0.894988E+01
    0.584315E+00
    O.105725E+01
                     -0.195635E+01
                                       O.886879E+O1
ο.
Ó.
٥.
ο.
ο.
                                       O.149971E+02
    0.214951E+01
                      O.981505E+01
    0.193940E+02
                     0.627022E+02
                                     0.635415E+02
                                       0.688610E+01
   -0.560015E+01
                     -0.487336E+01
                     -0.486003E+02
                                      -0.240117E+01
   -0.383867E+02
                      O.119337E+01
                                       0.746371E+01
   -0.586796E+01
                      0.113480E+02
   -0.207824E+02
                                       O.575569E+02
                                      -0.165995E+02
                     -O.985363E+O1
    0.575753E+01
   -0.884495E+02
                      O.587169E+02
                                      -0.434314E+03
                                       0.562981E+02
                      O.362257E+01
    0.294047E-01
   -0.484272E+03
                      O.117701E+04
                                       0.569748E+03
                                       0.0
                      0.0
    0.0
    0.0
                      0.0
                                       0.0
                                       0.0
    0.0
                      0.0
                                       0.0
    0.0
                      0.0
                                       0.0
    0.0
                      0.0
    0.0
                      0.0
                                       0.0
                                                                           ٥.
                                                                 0.
           ο.
                      ο.
                                Ο.
                                           ο.
                                                      ο.
ο.
                                                      ٥.
                                                                 ٥.
                                                                            ٥.
                                           ٥.
٥.
           ٥.
                      ٥.
                                 0.
                                           ο.
                                                      ο.
                                                                 ٥.
                                                                           ٥.
                      ٥.
                                 0.
ο.
           Ο.
                                                                            0.
                                                                 ο.
ο.
           ο.
                      ٥.
                                 0.
                                           0.
                                                      0.
Ο.
```

References

- Beard, R.V., "Failure Accommodation in Linear Systems Through Self-Reorganization," Ph.D. Thesis, Dept. of Aeronautics and Astronautics, M.I.T. Cambridge MA, Feb. 1971.
- 2. Jones, H.L., "Failure Detection in Linear Systems,"
 Ph.D. Thesis, Dept. of Aeronautics and Astronautics,
 M.I.T. Cambridge MA, Aug. 1973.
- 3. Meserole, J.S., "Detection Filters for Fault-Tolerant Control of Turbofan Engines," Ph.D. Thesis, Dept. of Aeronautics and Astronautics, M.I.T., Cambridge MA, June 1981.
- 4. Cole, S.R., Horner, G., and Montgomery, R., "Finite

 Element Analysis of Experimental Beam," NASA Langley

 Research Center, 1980.
- Parity Relations for Detection and Identification of Instrument Failures on a Free-free Beam," M.I.T.

 Space Systems Lab., Report #28-81, Sept. 1981.
- 6. VanderVelde, W.E., and Carignan, C.R., "A Dynamic Measure of Controllability and Observability for the Placement of Actuators and Sensors on Large Space Structures,"
 M.I.T. Space Systems Lab., Report #2-82, Jan. 1982.
- 7. Balas, M.J., "Active Control of Flexible Systems," Proc. of Dynamics and Control of Large Flexible Spacecraft Symposium, Blacksburg VA, June 1977.

- 8. VanderVelde, W.E., "Application of Failure Detection Filter Theory to Reliable Longitudinal Control of Guideway Vehicles," Report for U.S. Dept. of Transportation Contract No. DOT-TSC-1445, M.I.T.

 Cambridge MA, March 1979.
- 9. Gerard, J.P., "Application of Failure Detection Theory to Longitudinal Control of Guideway Vehicles," M.S. Thesis, Dept. of Aeronautics and Astronautics, M.I.T., Cambridge MA, June 1978.
- 10. Gustafson, D.E., and Speyer, J.L., "Linear Minimum Variance Filters Applied to Carrier Tracking,"

 Trans. on Auto. Control, Vol. AC-21, No. 1, Feb. 1976.
- 11. VanderVelde, J.E., "Reliability Issues in Active Control of Flexible Space Structures," Workshop on Structural Dynamics and Control of Large Space Structures, NASA Langley Research Center, Oct. 1980.

